arXiv:1304.3968v1 [math-ph] 15 Apr 2013

DIFFRACTION OF AN OBLIQUELY INCIDENT ELECTROMAGNETIC WAVE BY AN IMPEDANCE RIGHT-ANGLED CONCAVE WEDGE

Y.A. ANTIPOV
antipov@math.lsu.edu
Department of Mathematics, Louisiana State University
Baton Rouge LA 70803, USA

April 16, 2013

Abstract

Scattering of a plane electromagnetic wave by an anisotropic impedance concave wedge at skew incidence is analyzed. In the case of a right-angled wedge, the problem reduces to two symmetric order-2 vector Riemann-Hilbert problems (RHPs) which are solved exactly. The problem of matrix factorization leads to a scalar RHP on a genus-3 Riemann surface. Its closed-form solution is derived by the Weierstrass integrals, and the associated Jacobi inversion problem is solved in terms of elliptic integrals. It is shown that the solvability of the physical problem is governed by the location of the four zeros of the product of two quadratic polynomials associated with the two vector RHPs. The coefficients of these polynomials are expressed through the wave number, the impedance parameters and the angle of incidence. In the case when the solution is unique, the reflected, surface and diffracted waves are recovered.

1 Introduction

In diffraction theory the study of scattering of a plane obliquely incident electromagnetic wave from an anisotropic impedance wedge is one of the key canonical problems. In the case of normal incidence when the tensor impedance has zero diagonal and nonzero off-diagonal entries, the problem was solved in **(1)**. For oblique incidence, a closed-form solution is known for some special cases including the vector case for a half-plane **(2)**, **(3)**, **(4)**, the diagonal case for a wedge when the impedance parameters meet certain conditions, and the problem reduces to decoupled Maliuzhinets equations **(5)**, and the triangular case for a wedge when the impedance tensor allows for the reduction of the problem to two consequently solved scalar Maliuzhinets equations **(6)**.

Approximate solutions by the perturbation technique are available for the cases when the wedge is almost a half-plane **(7)** or when the incidence is almost normal **(8)**. Different approximate numerical solutions are available for the general case. They include those obtained by the method of integral equations **(9)**, **(10)**, the method of approximate matrix factorization in conjunction with the Fredholm integral equation theory **(11)**, and the probabilistic random walk method **(12)**. A method based on splitting the spectra into two functions, the solution of the Maliuzhinets equation and a function that is defined by a series whose coefficients solve a certain infinite system of linear algebraic equations, was recently proposed in **(13)**. By this method, the diffraction field in the case of scattering by the wedge of angle $3\pi/2$ was recovered in **(14)**. A method of reduction of wedge diffraction problems to functional equations was presented in **(15)**. In particular, it was pointed out that the electromagnetic problem for a right-angled convex wedge can be reduced to an order-6 vector RHP.

An exact solution for the general case of the tensor impedance and obliquely incident electromagnetic wave even for a right-angled wedge is still unavailable in the literature. Our goal in this paper is to derive a closed-form solution of the problem on an impenetrable right-angled concave wedge (of angle $3\pi/2$) in the case of oblique incidence when on the faces $S^\pm$ of the wedge the boundary conditions are

$$\pm\,\mathcal{E}_z = \eta^\pm_{\rho\rho} Z \mathcal{H}_\rho, \quad \mp\mathcal{E}_\rho = \eta^\pm_{zz} Z \mathcal{H}_z, \quad (\rho,\theta)\in S^\pm. \tag{1.1}$$

Here, $S^- = \{\theta = 0, 0 < \rho < \infty\}$, $S^+ = \{\theta = \pi/2, 0 < \rho < \infty\}$, $\mathcal{E}_\rho, \mathcal{H}_\rho$ and $\mathcal{E}_z, \mathcal{H}_z$ are the ρ- and z-components of the electromagnetic field, Z is the intrinsic impedance of the medium, and $\eta^\pm_{\rho\rho}$ and $\eta^\pm_{zz}$ are the impedance parameters.

In Section 2, we constitute the boundary value problem for the exterior of the concave wedge of an arbitrary angle, $W_e = \{0 < \rho < \infty, 0 < \theta < \alpha\}$ $(0 < \alpha < \pi)$, with the general impedance boundary conditions

$$\pm\,\mathcal{E}_z = \eta^\pm_{\rho\rho} Z \mathcal{H}_\rho + \eta^\pm_{\rho z} Z \mathcal{H}_z, \quad \mp\mathcal{E}_\rho = \eta^\pm_{z\rho} Z \mathcal{H}_\rho + \eta^\pm_{zz} Z \mathcal{H}_z, \quad (\rho,\theta)\in S^\pm. \tag{1.2}$$

Next, by applying the Laplace transform **(15)** we reduce the problem to two sets of six functional equations. We focus on the case $\alpha = \pi/2$, and in section 3, we reduce the functional equations to two vector RHPs with a 2×2 matrix coefficient. The solution to the second RHP is derived from the solution to the first RHP by a certain transformation of the impedance parameters and the angle of incidence $\beta \in (0,\pi)$. The solution of the RHP1 and RHP2, vectors $\Phi^\pm(\eta)$ and $\Psi^\pm(\eta)$, respectively, have to satisfy the symmetry conditions $\Phi^+(\eta) = \Phi^-(-\eta)$ and $\Psi^+(\eta) = \Psi^-(-\eta)$. It is shown that the matrix coefficient has the structure $G(\eta) = b_1(\eta)Q_1(\eta) + b_2(\eta)Q_2(\eta)$, where $b_1(\eta)$ and $b_2(\eta)$ are Hölder functions on the contour of the problem $L = \{-\infty, +\infty\}$, and $Q_1(\eta)$ and $Q_2(\eta)$ are polynomial 2×2 matrices. This case is algebraic, and the symmetric vector RHPs can be solved exactly **(16)**, **(17)**.

In section 4, for simplicity, we assume that the impedance parameters $\eta_{\rho z}$ and $\eta_{z\rho}$ vanish, that is the boundary conditions (1.2) become (1.1). For this case, we reduce the problem of matrix factorization to a scalar RHP on a genus-3 Riemann surface. The coefficient of the RHP on the first and second sheets coincides with the first and second eigenvalues of the matrix coefficient, and depending on the impedance parameters and the angle of incidence, the index of the quotient of the eigenvalues may be 0, 1 and -1. Because of the symmetry of the problem we manage to solve the associated Jacobi inversion problem in terms of elliptic integrals, and the solution to the matrix factorization problem is constructed in closed form by quadratures.

In section 5, we derive a closed-form solution to the vector RHPs. It turns out that the number of free constants in the general solution is governed by the location of zeros of a certain polynomial whose coefficients depend on the impedance parameters and the angle of incidence. The free parameters have to satisfy the symmetry conditions, additional mathematical and physical conditions. The results are summarized in Theorem 5.1 which implies that the solution is unique if and only if all the four zeros of the characteristic polynomial

$$p(\eta) = [(\eta^2 - k_0^2)\cos^2\beta - (\eta - \gamma_1^-)(\eta - \gamma_4^-)][(\eta^2 - k_0^2)\cos^2\beta - (\eta - \gamma_1^+)(\eta - \gamma_4^+)] \tag{1.3}$$

lie in the upper half-plane. Here, $\gamma_1^\pm = k(\eta^\pm_{\rho\rho})^{-1}\sin^2\beta$, $\gamma_4^\pm = k\eta^\pm_{zz}\sin^2\beta$. In the case of normal incidence, $\beta = \pi/2$, a simple closed-form solution is obtained, and the characteristic polynomial $p(\eta)$ reduces to $p(\eta) = (\eta - \gamma_1^-)(\eta - \gamma_1^+)(\eta - \gamma_4^-)(\eta - \gamma_4^+)$. The solution is unique if $\operatorname{Im}\gamma_j^\pm > 0$ $(j = 1, 4)$. This is consistent with the uniqueness theorem proved in **(18)** for an arbitrary wedge in the scalar case of normal incidence.

In section 6, we derive the spectra $S_e(s)$ and $S_h(s)$ of the problem and express the Sommerfeld integrals through the solution to the two vector RHPs. On continuing analytically the functions $S_e(s)$ and $S_h(s)$ to the right and to the left, applying the steepest descent method and the Cauchy theorem, we find the reflected, surface and diffracted waves.

2 Formulation: diffraction by a concave wedge of an arbitrary angle

Consider diffraction of an electromagnetic wave

$$\left(\mathcal{E}_z^{inc},\, \mathcal{H}_z^{inc}\right) = \left(E_z^i,\, H_z^i\right) e^{ikz\cos\beta - i\omega t}, \tag{2.1}$$

where

$$\left(E_z^i,\, H_z^i\right) = \left(E_0,\, H_0\right) e^{-ik\rho\cos(\theta-\theta_0)\sin\beta}, \tag{2.2}$$

by a wedge $W = \{0 < \rho < \infty, \alpha < \theta < 2\pi, |z| < \infty\}$, $\alpha \in (0, \pi)$, characterized by the impedance boundary conditions

$$\begin{aligned} \pm\mathcal{E}_z &= \eta_{\rho\rho}^{\pm} Z\mathcal{H}_\rho + \eta_{\rho z}^{\pm} Z\mathcal{H}_z \quad \text{on } S^{\pm}, \\ \mp\, \mathcal{E}_\rho &= \eta_{z\rho}^{\pm} Z\mathcal{H}_\rho + \eta_{zz}^{\pm} Z\mathcal{H}_z \quad \text{on } S^{\pm}. \end{aligned} \tag{2.3}$$

Here, k ($\operatorname{Im} k > 0$) is the wave number, ω is the angular velocity, $Z = \sqrt{\mu_0/\varepsilon_0}$ the intrinsic impedance of the medium, μ_0 is the magnetic permeability, ε_0 is the electric permittivity, $\eta_{\rho\rho}$, $\eta_{\rho z}$, $\eta_{z\rho}$ and η_{zz} are the impedance parameters. The symbols $S^{\pm}$ stand for the boundaries of the wedge, $S^{-} : \theta = 0, \rho > 0$, and $S^{+} : \theta = \alpha, \rho > 0$. Because of the representation (2.1) for the incident waves it is natural to split the electric and magnetic fields as

$$\left(\mathcal{E},\, \mathcal{H}\right) = \left(E,\, H\right) e^{ikz\cos\beta - i\omega t}. \tag{2.4}$$

By employing the Maxwell equations we eliminate the radial components of the electric and magnetic fields

$$\begin{aligned} E_\rho &= \frac{i}{k\sin^2\beta}\left[\cos\beta\frac{\partial}{\partial\rho}E_z + \frac{Z}{\rho}\frac{\partial}{\partial\theta}H_z\right], \\ ZH_\rho &= \frac{i}{k\sin^2\beta}\left[Z\cos\beta\frac{\partial}{\partial\rho}H_z - \frac{1}{\rho}\frac{\partial}{\partial\theta}E_z\right]. \end{aligned} \tag{2.5}$$

The resulting boundary conditions, after rearrangement, are formulated in terms of the z-components, $\phi_1 = E_z$ and $\phi_2 = ZH_z$, as

$$\begin{aligned} -\frac{i}{\rho}\frac{\partial\phi_1}{\partial\theta} + i\cos\beta\frac{\partial\phi_2}{\partial\rho} \mp \gamma_1^{\pm}\phi_1 + \gamma_2^{\pm}\phi_2 = 0 \quad \text{on } S^{\pm}, \\ i\cos\beta\frac{\partial\phi_1}{\partial\rho} + \frac{i}{\rho}\frac{\partial\phi_2}{\partial\theta} + \gamma_3^{\pm}\phi_1 \pm \gamma_4^{\pm}\phi_2 = 0 \quad \text{on } S^{\pm}, \end{aligned} \tag{2.6}$$

where

$$\begin{aligned} \gamma_1^{\pm} = \frac{k\sin^2\beta}{\eta_{\rho\rho}^{\pm}}, \quad \gamma_2^{\pm} = \frac{\eta_{\rho z}^{\pm}k\sin^2\beta}{\eta_{\rho\rho}^{\pm}}, \\ \gamma_3^{\pm} = \frac{\eta_{z\rho}^{\pm}k\sin^2\beta}{\eta_{\rho\rho}^{\pm}}, \quad \gamma_4^{\pm} = \frac{k\sin^2\beta}{\eta_{\rho\rho}^{\pm}}(\eta_{\rho\rho}^{\pm}\eta_{zz}^{\pm} - \eta_{\rho z}^{\pm}\eta_{z\rho}^{\pm}). \end{aligned} \tag{2.7}$$

In the exterior of the wedge, $W_e = \{0 < \rho < \infty, 0 < \theta < \alpha\}$, the functions ϕ_1 and ϕ_2 satisfy the Helmholtz equation. To convert the boundary value problem for the Helmholtz equation to a system of functional equations, we use the scheme **(15)**. On making the affine transformation of the Cartesian coordinates $u = x - y\cot\alpha$ and $v = y\csc\alpha$ we obtain that, in the new coordinates, the functions ϕ_1 and ϕ_2 are solutions of the differential equation in a quarter-plane

$$\left(\frac{\partial^2}{\partial u^2} + \frac{\partial^2}{\partial v^2} - 2\cos\alpha\frac{\partial^2}{\partial u\partial v} + k_0^2\sin^2\alpha\right)\phi_j = 0, \quad 0 < u, v < \infty, \quad j = 1, 2, \tag{2.8}$$

subject to the four boundary conditions

$$
\begin{gathered}
i\left(\frac{1}{\sin\alpha}\frac{\partial}{\partial u}-\cot\alpha\frac{\partial}{\partial v}\right)\phi_1+i\cos\beta\frac{\partial\phi_2}{\partial v}-\gamma_1^+\phi_1+\gamma_2^+\phi_2=0,\quad (u,v)\in\tilde{S}^+,\\
i\cos\beta\frac{\partial\phi_1}{\partial v}-i\left(\frac{1}{\sin\alpha}\frac{\partial}{\partial u}-\cot\alpha\frac{\partial}{\partial v}\right)\phi_2+\gamma_3^+\phi_1+\gamma_4^+\phi_2=0,\quad (u,v)\in\tilde{S}^+,\\
i\left(-\frac{1}{\sin\alpha}\frac{\partial}{\partial v}+\cot\alpha\frac{\partial}{\partial u}\right)\phi_1+i\cos\beta\frac{\partial\phi_2}{\partial u}+\gamma_1^-\phi_1+\gamma_2^-\phi_2=0,\quad (u,v)\in\tilde{S}^-,\\
i\cos\beta\frac{\partial\phi_1}{\partial u}+i\left(\frac{1}{\sin\alpha}\frac{\partial}{\partial v}-\cot\alpha\frac{\partial}{\partial u}\right)\phi_2+\gamma_3^-\phi_1-\gamma_4^-\phi_2=0,\quad (u,v)\in\tilde{S}^-,
\end{gathered}
\tag{2.9}
$$

where $k_0=k\sin\beta$, $\tilde{S}^+=\{(u,v)\in\mathbb{R}^2: u=0, v>0\}$, $\tilde{S}^-=\{(u,v)\in\mathbb{R}^2: v=0, u>0\}$. By means of the Laplace transform

$$
\tilde{\phi}_j(u,\eta)=\int\limits_0^\infty e^{i\eta v}\phi_j(u,v)dv \tag{2.10}
$$

the differential equation (2.8) may be put into the form

$$
\left(\frac{d^2}{du^2}+2i\eta\cos\alpha\frac{d}{du}+k_0^2\sin^2\alpha-\eta^2\right)\tilde{\phi}_j(u,\eta)=f_j(u),\quad j=1,2, \tag{2.11}
$$

where

$$
f_j(u)=\frac{\partial\phi_j}{\partial v}(u,0)-i\eta\phi_j(u,0)-2\cos\alpha\frac{\partial\phi_j}{\partial u}(u,0). \tag{2.12}
$$

The two roots of the characteristic equation of the differential operator in (2.11) are $-i\eta\cos\alpha\pm\sqrt{\eta^2-k_0^2}\sin\alpha$. Fix a branch $\zeta=\sqrt{\eta^2-k_0^2}$ of the two-valued function $\zeta^2=\eta^2-k_0^2$ by the condition $\zeta(0)=-ik_0$. The branch is a single-valued analytic function in the η-plane cut along the line joining the branch points $\pm k_0$ and passing through the infinite point. As $-\infty<\eta<+\infty$, the branch chosen possesses the property $\operatorname{Re}\zeta\geq 0$, and the general solution to equation (2.11) bounded as $u\to\infty$ has the form

$$
\tilde{\phi}_j(u,\eta)=A_j(\eta)e^{-\xi u}-\frac{1}{2\xi}\int_0^\infty e^{-|u-u_1|\xi}f_j(u_1)du_1,\quad j=1,2, \tag{2.13}
$$

where $\xi=-i\eta\cos\alpha+\zeta\sin\alpha$. To derive a functional equation for $\tilde{\phi}_j$, we apply the Laplace transform with respect to u using the function ξ as its parameter

$$
\hat{\phi}_j(i\xi,v)=\int_0^\infty e^{-\xi u}\phi_j(u,v)du. \tag{2.14}
$$

On referring to (2.12), we find that

$$
\int_0^\infty f_j(u)e^{-\xi u}du=\frac{d}{dv}\hat{\phi}_j(i\xi,0)-(i\eta+2\xi\cos\alpha)\hat{\phi}_j(i\xi,0)+2\cos\alpha\phi_j^\circ, \tag{2.15}
$$

where $\phi_j^\circ=\phi_j(0,0)$. On the other hand, from (2.13)

$$
\begin{gathered}
\tilde{\phi}_j(0,\eta)=A_j(\eta)-\frac{1}{2\xi}\int_0^\infty e^{-\xi u}f_j(u)du,\\
\frac{d\tilde{\phi}_j}{du}(0,\eta)=-\xi A_j(\eta)-\frac{1}{2}\int_0^\infty e^{-\xi u}f_j(u)du.
\end{gathered}
\tag{2.16}
$$

By excluding $A_j(\eta)$ and the Laplace transforms of the functions $f_j(u)$ and employing the second relation in (2.16) we get the following two equations:

$$\frac{d\tilde{\phi}_j}{du}(0,\eta)+\xi\tilde{\phi}_j(0,\eta)+\frac{d\hat{\phi}_j}{dv}(i\xi,0)-(i\eta+2\xi\cos\alpha)\hat{\phi}_j(i\xi,0)+2\cos\alpha\phi_j^\circ=0\quad j=1,2. \tag{2.17}$$

These two equations should be complemented by the Laplace-transformed boundary conditions. We apply the Laplace transform (2.10) to the boundary conditions (2.9) on the boundary $\tilde{S}^+$ and the transform (2.14) to the conditions on the side $\tilde{S}^-$. We have

$$i\csc\alpha\frac{d\tilde{\phi}_1}{du}(0,\eta)-(\gamma_1^++\eta\cot\alpha)\tilde{\phi}_1(0,\eta)+(\gamma_2^++\eta\cos\beta)\tilde{\phi}_2(0,\eta)+i\cot\alpha\phi_1^\circ-i\cos\beta\phi_2^\circ=0,$$

$$-i\csc\alpha\frac{d\tilde{\phi}_2}{du}(0,\eta)+(\gamma_3^++\eta\cos\beta)\tilde{\phi}_1(0,\eta)+(\gamma_4^++\eta\cot\alpha)\tilde{\phi}_2(0,\eta)-i\cos\beta\phi_1^\circ-i\cot\alpha\phi_2^\circ=0,$$

$$-i\csc\alpha\frac{d\hat{\phi}_1}{dv}(i\xi,0)+(\gamma_1^-+i\xi\cot\alpha)\hat{\phi}_1(i\xi,0)+(\gamma_2^-+i\xi\cos\beta)\hat{\phi}_2(i\xi,0)-i\cot\alpha\phi_1^\circ-i\cos\beta\phi_2^\circ=0,$$

$$i\csc\alpha\frac{d\hat{\phi}_2}{dv}(i\xi,0)+(\gamma_3^-+i\xi\cos\beta)\hat{\phi}_1(i\xi,0)-(\gamma_4^-+i\xi\cot\alpha)\hat{\phi}_2(i\xi,0)-i\cos\beta\phi_1^\circ+i\cot\alpha\phi_2^\circ=0. \tag{2.18}$$

Notice that by applying the Laplace transform (2.10) with respect to u and then the Laplace transform (2.14) with respect to v we obtain another set of six equations which coincide with (2.17) and (2.18) if we make the following transformation of the parameters and the functions:

$$\gamma_1^+\leftrightarrow\gamma_1^-,\quad \gamma_2^+\leftrightarrow-\gamma_2^-,\quad \gamma_3^+\leftrightarrow-\gamma_3^-,\quad \gamma_4^+\leftrightarrow\gamma_4^-,\quad \beta\to\pi-\beta,$$

$$\tilde{\phi}_j(0,\eta)\leftrightarrow\tilde{\phi}_j(\eta,0),\quad \frac{d\tilde{\phi}_j}{du}(0,\eta)\leftrightarrow\frac{d\tilde{\phi}_j}{dv}(\eta,0),$$

$$\hat{\phi}_j(i\xi,0)\leftrightarrow\hat{\phi}_j(0,i\xi),\quad \frac{d\hat{\phi}_j}{dv}(i\xi,0)\leftrightarrow\frac{d\hat{\phi}_j}{du}(0,i\xi),\quad j=1,2. \tag{2.19}$$

3 Vector RHPs in the case of a right-angled concave wedge

Consider the case $\alpha=\pi/2$ (Fig. 1) and reduce the system of six functional equations (2.17), (2.18) and the one obtained from the system (2.17), (2.18) by the transformation (2.19) to two symmetric RHPs with a 2×2 matrix coefficient. If the domain of interest is a quarter-plane, then the standard Cartesian coordinates $x=u$, $y=v$ can be employed, and $\xi=\zeta$, $\zeta=\sqrt{\eta^2-k_0^2}$. We split the incident waves E_z^i and H_z^i into two waves

$$\begin{pmatrix}E_z^{i+}, & H_z^{i+}\end{pmatrix}=\begin{pmatrix}E_0, & H_0\end{pmatrix}e^{-ik_0\rho\cos(\theta-\theta_0)}\omega(\theta;\theta_0,\pi/2),$$

$$\begin{pmatrix}E_z^{i-}, & H_z^{i-}\end{pmatrix}=\begin{pmatrix}E_0, & H_0\end{pmatrix}e^{-ik_0\rho\cos(\theta-\theta_0)}\omega(\theta;0,\theta_0), \tag{3.1}$$

where

$$\omega(\theta;a,b)=\begin{cases}1, & a<\theta<b,\\ 0, & \text{otherwise}.\end{cases} \tag{3.2}$$

Consider first the problem associated with the incident wave (E_z^{i+},H_z^{i+}). From the boundary conditions (2.18) we express the derivatives $d\tilde{\phi}_j(0,\eta)/dx$ and $d\hat{\phi}_j(i\zeta,0)/dy$ through the functions $\tilde{\phi}_j(0,\eta)$ and $\hat{\phi}_j(i\zeta,0)$ $(j=1,2)$. Then, on replacing η by $-\eta$ in (2.17) we obtain two more equations

$$\frac{d\tilde{\phi}_j}{dx}(0,-\eta)+\zeta\tilde{\phi}_j(0,-\eta)+\frac{d\hat{\phi}_j}{dy}(i\zeta,0)+i\eta\hat{\phi}_j(i\zeta,0)=0,\quad j=1,2. \tag{3.3}$$



Figure 1: Geometry of the problem on a right-angled concave wedge.

These two extra equations in conjunction with (2.17) allow us to express the functions $\hat{\phi}_j(i\zeta, 0)$ through the functions $\tilde{\phi}_j(0, \pm\eta)$

$$\hat{\phi}_1(i\zeta, 0) = -\frac{\gamma_1^+ + i\zeta}{2\eta}[\tilde{\phi}_1(0, \eta) - \tilde{\phi}_1(0, -\eta)] + \frac{\gamma_2^+ + \eta\cos\beta}{2\eta}\tilde{\phi}_2(0, \eta) + \frac{-\gamma_2^+ + \eta\cos\beta}{2\eta}\tilde{\phi}_2(0, -\eta),$$

$$\hat{\phi}_2(i\zeta, 0) = -\frac{\gamma_3^+ + \eta\cos\beta}{2\eta}\tilde{\phi}_1(0, \eta) + \frac{\gamma_3^+ - \eta\cos\beta}{2\eta}\tilde{\phi}_1(0, -\eta) - \frac{\gamma_4^+ + i\zeta}{2\eta}[\tilde{\phi}_2(0, \eta) - \tilde{\phi}_2(0, -\eta)]. \quad (3.4)$$

On substituting the expressions for the functions $\hat{\phi}_j(i\zeta, 0)$ and the derivatives $d\tilde{\phi}_j(0, \eta)/du$ and $d\hat{\phi}_j(i\zeta, 0)/dv$ in equations (2.17) we ultimately obtain

$$A(\eta)\Phi^+(\eta) + B(\eta)\Phi^+(-\eta) = 0, \quad \eta \in L = (-\infty, +\infty), \quad (3.5)$$

where

$$\Phi^+(\eta) = \begin{pmatrix} \tilde{\phi}_1(0, \eta) \\ \tilde{\phi}_2(0, \eta) \end{pmatrix}, \quad A(\eta) = \begin{pmatrix} a_{11}(\eta) & a_{12}(\eta) \\ a_{21}(\eta) & a_{22}(\eta) \end{pmatrix}, \quad B(\eta) = \begin{pmatrix} b_{11}(\eta) & b_{12}(\eta) \\ b_{21}(\eta) & b_{22}(\eta) \end{pmatrix},$$

$$a_{11} = \delta_{1+}(\eta)[1 - \delta_{1-}(\eta)] - \delta_{2-}(\eta)\delta_{3+}(\eta), \quad a_{12} = -\delta_{2+}(\eta)[1 - \delta_{1-}(\eta)] - \delta_{2-}(\eta)\delta_{4+}(\eta),$$

$$a_{21} = \delta_{3+}(\eta)[1 - \delta_{4-}(\eta)] + \delta_{3-}(\eta)\delta_{1+}(\eta), \quad a_{22} = \delta_{4+}(\eta)[1 - \delta_{4-}(\eta)] - \delta_{3-}(\eta)\delta_{2+}(\eta),$$

$$b_{11} = \delta_{1-}(\eta)\delta_{1+}(-\eta) + \delta_{2-}(\eta)\delta_{3+}(-\eta), \quad b_{12} = -\delta_{1-}(\eta)\delta_{2+}(-\eta) + \delta_{2-}(\eta)\delta_{4+}(-\eta),$$

$$b_{21} = -\delta_{3-}(\eta)\delta_{1+}(-\eta) + \delta_{4-}(\eta)\delta_{3+}(-\eta), \quad b_{22} = \delta_{3-}(\eta)\delta_{2+}(-\eta) + \delta_{4-}(\eta)\delta_{4+}(-\eta),$$

$$\delta_{j+}(\eta) = \gamma_j^+ + i\zeta, \quad \delta_{j-}(\eta) = \frac{\gamma_j^- + \eta}{2\eta}, \quad j = 1, 4,$$

$$\delta_{j+}(\eta) = \gamma_j^+ + \eta\cos\beta, \quad \delta_{j-}(\eta) = \frac{\gamma_j^- + i\zeta\cos\beta}{2\eta}, \quad j = 2, 3. \quad (3.6)$$

It can be directly verified that $A(\eta) = B(-\eta)$ for all η. Denote $\Phi^-(\eta) = \Phi^+(-\eta)$ and let $\eta_0 = k_0 \sin\theta_0$. Then the vectors $\Phi^\pm(\eta)$ constitute the solution to the following symmetric RHP.

RHP 1. Find two vectors $\Phi^{\pm}(\eta)$ *analytic everywhere in the half-planes* $\mathbb{C}^{\pm}: \pm \operatorname{Im}\eta > 0$ *except at the simple poles* $\eta = \pm\eta_0$,

$$\operatorname*{res}_{\eta=\eta_0} \Phi_1^+(\eta) = iE_0, \quad \operatorname*{res}_{\eta=\eta_0} \Phi_2^+(\eta) = iZH_0, \tag{3.7}$$

and continuous up the the real axis L. *At the contour* L, *their limit values satisfy the boundary condition*

$$\Phi^+(\eta) = G(\eta)\Phi^-(\eta), \quad \eta \in L, \tag{3.8}$$

where $G(\eta) = -[A(\eta)]^{-1}B(\eta)$. *At infinity, both vectors vanish, and everywhere in the plane they meet the symmetry condition* $\Phi^+(\eta) = \Phi^-(-\eta)$.

The same derivations can be applied to the case of the incident wave (E_z^{i-}, H_z^{i-}). On making the transformations (2.19) in the system (2.17), (2.18) we arrive at the second RHP.

RHP 2. Find two vectors $\Psi^{\pm}(\eta)$ *analytic everywhere in the half-planes* $\mathbb{C}^{\pm}$ *except at the simple poles* $\eta = \pm\tilde{\eta}_0$, $\tilde{\eta}_0 = k_0 \cos\theta_0$,

$$\operatorname*{res}_{\eta=\tilde{\eta}_0} \Psi_1^+(\eta) = iE_0, \quad \operatorname*{res}_{\eta=\tilde{\eta}_0} \Psi_2^+(\eta) = iZH_0, \tag{3.9}$$

and continuous up the real axis L. *At the contour* L, *their limit values satisfy the boundary condition*

$$\Psi^+(\eta) = \tilde{G}(\eta)\Psi^-(\eta), \quad \eta \in L, \tag{3.10}$$

where $\Psi_j^+(\eta) = \tilde{\phi}_j(\eta, 0)$, $\Psi_j^-(\eta) = \Psi_j^+(-\eta)$, $j = 1, 2$, *and* $\tilde{G}(\eta)$ *is the matrix* $G(\eta)$ *whose parameters* $\gamma_j^{\pm}$ $(j = 1, \ldots, 4)$ *and* β *are transformed by (2.19). At infinity, both vectors,* $\Psi^+(\eta)$ *and* $\Psi^-(\eta)$, *vanish.*

It is sufficient to solve the RHP 1. The solution to the RHP 2 can be derived by the transformation (2.19). Notice that the matrix coefficient of the RHP admits the representation

$$G(\eta) = \frac{1}{d(\eta)}[G^0(\eta) + \zeta G^1(\eta)], \tag{3.11}$$

where $d(\eta)$ is a scalar, G^0 and G^1 are 2×2 polynomial matrices, and $\det G(\eta) \neq 0$, $\eta \in L$. It is known (Antipov, 2010) that any nonsingular matrix of such a structure can be factorized by reducing the vector RHP to a scalar RHP on a Riemann surface of the associated algebraic function. To simplify our derivations, it will be helpful to assume that either $\gamma_2^{\pm} = \gamma_3^{\pm} = 0$ and the angle β is arbitrary, or that all the four impedance parameters $\gamma_j^{\pm}$ are arbitrary and $\beta = \pi/2$. In what follows we consider the former case, namely, $\gamma_2^{\pm} = \gamma_3^{\pm} = 0$, $\beta \in (0, \pi)$.

Before beginning factorization of the matrix $G(\eta)$, we notice that the matrix $G(\eta)$ is continuous everywhere in the contour L, and as $\eta \to \pm\infty$, $G(\eta) \sim \operatorname{diag}\{-1, -1\}$. Compute first the index of its determinant

$$\kappa_0 = \frac{1}{2\pi}[\arg \det G(\eta)]_{-\infty}^{\infty}, \tag{3.12}$$

which has the form

$$\det G(\eta) = \frac{\delta_0(-\eta)}{\delta_0(\eta)}, \tag{3.13}$$

and

$$\delta_0(\eta) = (\eta^2 - k_0^2)\cos^2\beta - (\eta - \gamma_1^-)(\eta - \gamma_4^-). \tag{3.14}$$

We distinguish the following three cases:

(i) the two zeros of the quadratic polynomial $\delta_0(\eta)$ lie in the lower half-plane, $\delta_0(\eta) = -(\eta + \tau_1)(\eta + \tau_2)\sin^2\beta$, $\operatorname{Im}\tau_j > 0$, $j = 1, 2$,

(ii) the zeros lie in the opposite half-planes, $\delta_0(\eta) = -(\eta - \tau_1)(\eta + \tau_2)\sin^2\beta$, $\operatorname{Im}\tau_j > 0$, $j = 1, 2$, and

(iii) both zeros lie in the upper half-plane, $\delta_0(\eta) = -(\eta - \tau_1)(\eta - \tau_2)\sin^2\beta$, $\operatorname{Im}\tau_j > 0$, $j = 1, 2$.

By the argument principle, in case (i), $\kappa_0 = 2$ (in the upper half-plane, the function $\delta_0(-\eta)$ has two zeros, while the function $\delta_0(\eta)$ has no zeros in $\mathbb{C}^+$). In case (ii), $\kappa_0 = 0$, and in the last case, $\kappa_0 = -2$.

Our next step is to rearrange the representation (3.11) as

$$G(\eta) = \frac{\zeta}{\delta_0(\eta)\delta_1(\eta)} G^1(\eta) \left[I + \frac{1}{\zeta d_1(\eta)} \begin{pmatrix} r_1(\eta) & r_2(\eta) \\ r_3(\eta) & r_4(\eta) \end{pmatrix} \right], \tag{3.15}$$

where I is the unit 2×2 matrix, $r_j(\eta)$ $(j = 1, \ldots, 4)$ are polynomials,

$$\delta_1(\eta) = (\gamma_1^+ + i\zeta)(\gamma_4^+ + i\zeta) + \eta^2\cos^2\beta, \tag{3.16}$$

the entries $g^1_{st}(\eta)$ of the polynomial matrix $G^1(\eta)$ are

$$g^1_{jj}(\eta) = -i(\gamma_1^+ + \gamma_4^+)[k_0^2\cos^2\beta - \eta^2\sin^2\beta + (-1)^j\eta(\gamma_1^- - \gamma_4^-) + \gamma_1^-\gamma_4^-], \quad j = 1, 2,$$

$$g^1_{12}(\eta) = -2i\eta\cos\beta[\gamma_1^-\gamma_4^- - (\gamma_4^+)^2 - k_0^2\sin^2\beta],$$
$$g^1_{21}(\eta) = 2i\eta\cos\beta[\gamma_1^-\gamma_4^- - (\gamma_1^+)^2 - k_0^2\sin^2\beta], \tag{3.17}$$

and $d_1(\eta) = \det G^1(\eta)$ is a degree-4 even polynomial

$$d_1(\eta) = \alpha_0 + \alpha_1\eta^2 + \alpha_2\eta^4, \tag{3.18}$$

whose coefficients are

$$\alpha_0 = -(\gamma_1^+ + \gamma_4^+)^2(\gamma_1^-\gamma_4^- + k_0^2\cos^2\beta)^2, \quad \alpha_2 = -(\gamma_1^+ + \gamma_4^+)^2\sin^4\beta,$$

$$\alpha_1 = (\gamma_1^+ + \gamma_4^+)^2[(\gamma_1^-)^2 + (\gamma_4^-)^2 - 2k_0^2\cos^4\beta] + \{-4(\gamma_1^-\gamma_4^-)^2 - (2\gamma_1^+\gamma_4^+ - k_0^2)^2$$
$$+ 2\gamma_1^-\gamma_4^-[(\gamma_1^+ - \gamma_4^+)^2 + 2k_0^2] + 2k_0^2[(\gamma_1^+)^2 - 2\gamma_1^-\gamma_4^- + (\gamma_4^+)^2 + k_0^2]\cos 2\beta - k_0^4\cos^2 2\beta\}\cos^2\beta. \tag{3.19}$$

It is an easy matter now to represent the matrix $G(\eta)$ in the form

$$G(\eta) = \frac{\delta_*\sqrt{\Delta(\eta)}}{\delta_0(\eta)} G^1(\eta)\Gamma(\eta), \tag{3.20}$$

where δ_* is a constant to be determined,

$$\Gamma(\eta) = \begin{pmatrix} b_0(\eta) + c_0(\eta)l(\eta) & c_0(\eta)m(\eta) \\ c_0(\eta)n(\eta) & b_0(\eta) - c_0(\eta)l(\eta) \end{pmatrix},$$

$$b_0 = \frac{b}{\sqrt{\Delta}}, \quad c_0 = \frac{c}{\sqrt{\Delta}}, \quad \Delta = b^2 - c^2 f, \quad f = l^2 + mn,$$

$$b = \frac{\zeta}{\delta_*\delta_1}\left(1 + \frac{r}{\zeta d_1}\right), \quad c = \frac{i\hat{\gamma}\eta\cos\beta}{\delta_*\delta_1 d_1},$$

$$\hat{\gamma} = \gamma_1^-\gamma_4^- + \gamma_1^+\gamma_4^+ - k_0^2\sin^2\beta, \tag{3.21}$$

and l, m, n and r are polynomials,

$$l(\eta) = \eta\cos\beta[\eta^2(\gamma_1^+ - \gamma_4^+) - 2\eta(\gamma_1^- - \gamma_4^-)(\gamma_1^+ + \gamma_4^+)$$

$$
\begin{aligned}
&+(\gamma_1^+-\gamma_4^+)(2\gamma_1^-\gamma_4^- - 3k_0^2) - (\gamma_1^+-\gamma_4^+)(\eta^2-k_0^2)\cos 2\beta],\\
&m(\eta) = -\frac{3}{4}\eta^4 + \eta^3(\gamma_1^- - \gamma_4^-) + 2\eta(\gamma_1^- - \gamma_4^-)[(\gamma_4^+)^2 - k_0^2]\\
&+[(\gamma_4^+)^2 - k_0^2](2\gamma_1^-\gamma_4^- + k_0^2) + \frac{3}{4}\eta^2[4\gamma_1^-\gamma_4^- - 4(\gamma_4^+)^2 + k_0^2] - \frac{1}{4}\eta^2(\eta^2-k_0^2)\cos 4\beta\\
&+\{\eta^4 - \eta^3(\gamma_1^- - \gamma_4^-) + \eta^2[\gamma_1^-\gamma_4^- - (\gamma_4^+)^2 - k_0^2] + k_0^2[(\gamma_4^+)^2 - k_0^2]\}\cos 2\beta, \qquad (3.22)
\end{aligned}
$$

the polynomial $n(\eta)$ coincides with $-m(\eta)$ if γ_1^- and γ_1^+ are replaced by γ_4^- and γ_4^+, respectively, and

$$
\begin{aligned}
&r(\eta) = \frac{i}{16}(\gamma_1^+ + \gamma_4^+)[-\eta^2 + 2(\gamma_1^+\gamma_4^+ + k_0^2) + \eta^2\cos 2\beta]\\
&\times[3\eta^4 - 8\eta^2(\gamma_1^-)^2 - 8\eta^2\gamma_1^-\gamma_4^- - 8\eta^2(\gamma_4^-)^2 + 8(\gamma_1^-)^2(\gamma_4^-)^2 + 2\eta^2k_0^2\\
&+8\gamma_1^-\gamma_4^-k_0^2 + 3k_0^4 - 4(\eta^2-k_0^2)(\eta^2 + 2\gamma_1^-\gamma_4^- + k_0^2)\cos 2\beta + (\eta^2-k_0^2)^2\cos 4\beta]. \qquad (3.23)
\end{aligned}
$$

In (3.21) we divided the coefficients of the matrix $\Gamma(\eta)$ by $\sqrt{\Delta(\eta)}$ ($\sqrt{\Delta(\eta)}$ is a fixed branch of the function $\Delta^{1/2}(\eta)$) and in (3.20) we multiplied the matrix $\Gamma(\eta)$ by the same factor. This transformation implies $\det\Gamma(\eta) = 1$ for all $\eta \in L$ and simplifies the solution. Notice that from (3.20),

$$
\det G(\eta) = \frac{\delta_*^2\Delta(\eta)d_1(\eta)}{\delta_0^2(\eta)}. \qquad (3.24)
$$

On comparing (3.24) and (3.13), we obtain that $\Delta(\eta)$ is a rational even function

$$
\Delta(\eta) = \frac{\delta_0(\eta)\delta_0(-\eta)}{\delta_*^2 d_1(\eta)}. \qquad (3.25)
$$

By the argument principle, its index is equal to 0.

4 Scalar RHP on a Riemann surface

4.1 Statement of the problem

Since $G^1(\eta)$ is a polynomial matrix, the problem of factorization of the matrix $G(\eta)$ reduces to the one for the matrix $\Gamma(\eta)$. Its factorization can be expressed through the solution of the associated scalar RHP on the genus-3 Riemann surface $\mathfrak{R}$ of the algebraic function $w^2 = f(\eta)$. The function $f(\eta)$ is an even degree-8 polynomial which has the form

$$
f(\eta) = h_0 + h_1\eta^2 + h_2\eta^4 + h_3\eta^6 + h_4\eta^8, \qquad (4.1)
$$

where

$$
\begin{aligned}
&h_0 = -4u_1u_2u_3^2, \quad h_4 = -4\sin^8\beta,\\
&h_1 = 4(\gamma_1^- - \gamma_4^-)^2u_1u_2 + (\gamma_1^+ - \gamma_4^+)^2(2\gamma_1^-\gamma_4^- - 3k_0^2 + k_0^2\cos 2\beta)^2\cos^2\beta - 2u_3\\
&\times\{u_2[(\gamma_1^-\gamma_4^- - (\gamma_1^+)^2)(\cos 2\beta + 3) + 2k_0^2\sin^4\beta] + u_1[(\gamma_1^-\gamma_4^- - (\gamma_4^+)^2)(\cos 2\beta + 3) + 2k_0^2\sin^4\beta]\},\\
&h_2 = 4u_4^+u_4^- + 8(\gamma_1^-\gamma_4^-u_4^+ + \gamma_1^+\gamma_4^+u_4^-)\cos^2\beta + 8\gamma_1^-\gamma_1^+\gamma_4^-\gamma_4^+\cos^2\beta(\cos 2\beta - 3)\\
&-[(\gamma_1^-\gamma_4^-)^2 + (\gamma_1^+\gamma_4^+)^2](\cos 2\beta + 3)^2 + 2k_0^2\sin^2\beta\{-u_4^+(3\cos 2\beta + 1)\\
&+2\cos^2\beta[-2\gamma_1^+\gamma_4^+(\cos 2\beta - 3) + \gamma_1^-\gamma_4^-(\cos 2\beta + 3)] - 4u_4^- - 2k_0^2\sin^2\beta(1 + \cos^4\beta)\},\\
&h_3 = 4\sin^4\beta[u_4^- - u_4^+ + 2(\gamma_1^-\gamma_4^- - \gamma_1^+\gamma_4^+)\cos^2\beta + 2k_0^2\sin^4\beta],
\end{aligned}
$$

$$u_1 = (\gamma_1^+)^2 - k_0^2, \quad u_2 = (\gamma_4^+)^2 - k_0^2, \quad u_3 = \gamma_1^-\gamma_4^- + k_0^2\cos^2\beta, \quad u_4^\pm = (\gamma_1^\pm)^2 + (\gamma_4^\pm)^2. \tag{4.2}$$

Let $\pm a_j$ $(j = 1, 2, 3, 4)$ be the eight branch point of the function $\sqrt{f(\eta)}$ (they are determined explicitly by radicals) such that $0 < \operatorname{Im} a_1 < \operatorname{Im} a_2 < \operatorname{Im} a_3 < \operatorname{Im} a_4$. Cut the plane along the segments $l_1^\pm$ and $l_2^\pm$ with the starting points $\pm a_1$ and $\pm a_3$ and the terminal points $\pm a_2$ and $\pm a_4^\pm$, respectively. Fix the single branch of the function $\sqrt{f(\eta)}$ as follows:

$$\sqrt{f(\eta)} = 2i\sin^4\beta \prod_{j=1}^4 \sqrt{\rho_j^+\rho_j^-}\, e^{i(\varphi_j^+ + \varphi_j^-)/2}, \tag{4.3}$$

where $\rho_j^\pm = |\eta \mp a_j|$, $\varphi_j^\pm = \arg(\eta \mp a_j)$, $\varphi_j^+ \in (-\pi, 0)$, $\varphi_j^- \in (0, \pi)$, $\eta \in L$, $j = 1, 2, 3, 4$.

The genus-3 hyperelliptic surface $\mathfrak{R}$ is formed by two copies, $\mathbb{C}_1$ and $\mathbb{C}_2$, of the extended η-plane $\mathbb{C} \cup \{\infty\}$ cut along the segments $l_1^\pm$ and $l_2^\pm$. The two sheets are glued according to the rule

$$w = \begin{cases} \sqrt{f(\eta)}, & \eta \in \mathbb{C}_1, \\ -\sqrt{f(\eta)}, & \eta \in \mathbb{C}_2. \end{cases} \tag{4.4}$$

Let $\lambda(\eta, w)$ be a new function defined on the surface $\mathfrak{R}$ as

$$\lambda(\eta, w) = \begin{cases} \lambda_1(\eta), & \eta \in \mathbb{C}_1, \\ \lambda_2(\eta), & \eta \in \mathbb{C}_2, \end{cases} \tag{4.5}$$

where $\lambda_1(\eta) = b_0(\eta) + c_0(\eta)\sqrt{f(\eta)}$ and $\lambda_1(\eta) = b_0(\eta) - c_0(\eta)\sqrt{f(\eta)}$ are the eigenvalues of the matrix $\Gamma(\eta)$. We find it convenient to introduce two matrices, Y and Q, as

$$Y(\eta, w) = \frac{1}{2}\left[I + \frac{1}{w}Q(\eta)\right], \quad Q(\eta) = \begin{pmatrix} l(\eta) & m(\eta) \\ n(\eta) & -l(\eta) \end{pmatrix}. \tag{4.6}$$

Then a solution to the matrix factorization problem

$$\Gamma(\eta) = X^+(\eta)[X^-(\eta)]^{-1}, \quad \eta \in L, \tag{4.7}$$

may be expressed through a nontrivial solution to the following scalar RHP on the surface $\mathfrak{R}$.

Find a function $\chi(\eta, w)$ piece-wise analytic on the surface $\mathfrak{R} \setminus \mathfrak{L}$, $\mathfrak{L} = (L \subset \mathbb{C}_1) \cup (L \subset \mathbb{C}_2)$, except for at most a finite number of poles, continuous up to the contour $\mathfrak{L}$, bounded at both infinite points of the surface $\mathfrak{R}$ and satisfying the boundary condition

$$\chi^+(\eta, w) = \lambda(\eta, w)\chi^-(\eta, w), \quad (\eta, w) \in \mathfrak{L}. \tag{4.8}$$

In terms of the solution of the RHP (4.8), the matrix $X(\eta)$ and its inverse are given by

$$X(\eta) = \chi(\eta, w)Y(\eta, w) + \chi(\eta, -w)Y(\eta, -w), \quad \eta \in \mathbb{C}^\pm.$$

$$[X(\eta)]^{-1} = \frac{Y(\eta, w)}{\chi(\eta, w)} + \frac{Y(\eta, -w)}{\chi(\eta, -w)}, \quad \eta \in \mathbb{C}^\pm. \tag{4.9}$$

4.2 Solution with an essential singularity at infinity

The chief difficulty in the procedure of matrix factorization based on the use of the solution of the scalar RHP on a Riemann surface (4.8) arises in the necessity of constructing a meromorphic solution with explicitly determined poles and zeros. In order to derive such a solution, we consider the function

$$\chi_0(\eta, w) = \exp\{\psi_0(\eta, w)\}, \quad (\eta, w) \in \mathfrak{R}, \tag{4.10}$$

where $\psi_0(\eta, w)$ is the Weierstrass integral

$$\psi_0(\eta, w) = \frac{1}{2\pi i}\int_{\mathfrak{L}} \log\lambda(t,\xi)\frac{w+\xi}{2\xi}\frac{dt}{t-\eta}, \tag{4.11}$$

and $\xi = w(t)$, $t \in \mathfrak{L}$. This integral over the contour $\mathcal{L}$ on the surface $\mathfrak{R}$ can be transformed into two integrals over the contour L in the η-plane as

$$\psi_0(\eta, w) = \frac{1}{4\pi i}\int_L [\log\lambda_1(t) + \log\lambda_2(t)]\frac{dt}{t-\eta} + \frac{w}{4\pi i}\int_L [\log\lambda_1(t) - \log\lambda_2(t)]\frac{dt}{\sqrt{f(t)}(t-\eta)}. \tag{4.12}$$

To simplify this representation, we study the eigenvalues λ_j of the matrix $\Gamma(\eta)$. Referring to (3.21), we obtain that $b(\eta) = b(-\eta)$, $c(\eta) = -c(-\eta)$ and also

$$\lambda_1(\eta)\lambda_2(\eta) = \det\Gamma(\eta) = 1, \quad \frac{\lambda_1(\eta)}{\lambda_2(\eta)} = \frac{b(\eta)+c(\eta)\sqrt{f(\eta)}}{b(\eta)-c(\eta)\sqrt{f(\eta)}} = \frac{\lambda_2(-\eta)}{\lambda_1(-\eta)}. \tag{4.13}$$

As $\eta \to \infty$,

$$b(\eta) = -\frac{i}{\delta_*(\gamma_1^+ + \gamma_4^+)} + O(\eta^{-1}), \quad c(\eta) \sim -\frac{\hat{\gamma}\cos\beta}{\eta^5(\gamma_1^+ + \gamma_4^+)\sin^6\beta}, \quad \eta \to \infty. \tag{4.14}$$

On putting $\delta_* = -i(\gamma_1^+ + \gamma_4^+)^{-1}$, we have $b(\eta) = 1 + O(\eta^{-1})$, $\eta \to \infty$. At zero and at infinity, the function $\lambda_1(\eta)/\lambda_2(\eta)$ has the following properties:

$$\frac{\lambda_1(0)}{\lambda_2(0)} = 1, \quad \frac{\lambda_1(\eta)}{\lambda_2(\eta)} = 1 + O(\eta^{-1}), \quad \eta \to \infty. \tag{4.15}$$

It has also been established that $\lambda_1(\eta)$ and $\lambda_2(\eta)$ are bounded and do not vanish on the contour L. On fixing the branches of the functions $\log\lambda_1(\eta)$ and $\lambda_2(\eta)$ as $\log\lambda_1(\infty) = \log\lambda_2(\infty) = 0$ we obtain that $\log\lambda_2(\eta) = -\log\lambda_1(\eta)$ for all $\eta \in L$ and therefore

$$\psi_0(\eta, w) = \frac{w}{4\pi i}\int_L \frac{\varepsilon(t)dt}{\sqrt{f(t)}(t-\eta)}. \tag{4.16}$$

where

$$\varepsilon(\eta) = \log l(\eta), \quad l(\eta) = \frac{\lambda_1(\eta)}{\lambda_2(\eta)}, \tag{4.17}$$

and the branch of the logarithmic function is fixed by the condition $\varepsilon(\infty) = 0$. To establish whether the function $\varepsilon(\eta)$ is continuous in the contour L, we study next the increment of the argument of the function $l(\eta)$ when η traverses the contour L in the positive direction. Introduce the index of the function $l(\eta)$

$$\operatorname{ind} l(\eta) = \frac{1}{2\pi}[\arg l(\eta)]_{-\infty}^{\infty}. \tag{4.18}$$



Figure 2: Parametrically defined function $l(\eta)$, $0 \leq \eta < +\infty$, in case (i, section 3) when $k_0 = 1 + 0.1i$, $\beta = \pi/4$. Case a: $\kappa_0 = 0$ ($\gamma_1^+ = 1 - i$, $\gamma_4^+ = 1 + 2i$, $\gamma_1^- = 1 - 2i$, $\gamma_4^- = 1 - 3i$). Case b: $\kappa_0 = 0$ ($\gamma_1^+ = 2 + i$, $\gamma_4^+ = 1 + 2i$, $\gamma_1^- = 1 - i$, $\gamma_4^- = 1 - 2i$). Case c: $\kappa_0 = 1$ (the anticlockwise direction, $\gamma_1^+ = -1 + i$, $\gamma_4^+ = -1 + 2i$, $\gamma_1^- = -1 - 0.1i$, $\gamma_4^- = -1 - 0.2i$). Case d: $\kappa_0 = -1$ (the clockwise direction, $\gamma_1^+ = 1 + i$, $\gamma_4^+ = 1 - i$, $\gamma_1^- = 1 - 0.3i$, $\gamma_4^- = 1 - i$).

Due to the fact that $\lambda_2(-\eta) = \lambda_1(\eta)$, the function $\varepsilon(\eta)$ is odd, and the index of the function $l(\eta)$ is an even number, $\operatorname{ind} l(\eta) = 2\kappa_0$. If $\kappa_0 = 0$, then the function $\varepsilon(\eta)$ is continuous at the point $\eta = 0$, otherwise it is discontinuous at $\eta = 0$. Notice also that

$$\kappa_0 = \frac{1}{2\pi}[\arg \lambda_1(\eta)]_{-\infty}^{\infty} = \frac{1}{2\pi}\left[\arg \frac{\lambda_1(\eta)}{\lambda_2(\eta)}\right]_0^{\infty}. \tag{4.19}$$

Numerical computations implemented for different sets of the problem parameters k_0, β, $\gamma_1^\pm$ and $\gamma_4^\pm$ show that κ_0 may be 0, 1, or -1. Figure 2 shows the graphs of the function $l(\eta)$ for $0 \leq \eta < +\infty$ in the plane $(\operatorname{Re} l(\eta), \operatorname{Im} l(\eta))$ for some values of the problem parameters in case (i) when both zeros of the polynomial $\delta_0(\eta)$ lie in the lower half-plane. The graphs of the function $l(\eta)$ for some values of the problem parameters in cases (ii) when the two zeros of $\delta_0(\eta)$ lie in the opposite half-planes are given in Figures 3a and 3b. Figures 3c and 3d illustrate case (iii) (both zeros lie in the upper half-plane) when index κ_0 vanishes and equals -1, respectively. In the last case η traverses the contour around the origin in the negative direction.

Due to the choice of the branch of the logarithmic function $\log l(\eta)$, if $\kappa_0 = 1$, then $\varepsilon(0^\pm) = \mp 2\pi i$, $\varepsilon(0^\pm) = \pm 2\pi i$ when $\kappa_0 = -1$, and $\varepsilon(\pm 0) = 0$ in the case $\kappa_0 = 0$. Transform now the integral (4.12) into the form

$$\psi_0(\eta, w) = \frac{w}{2\pi i}\int_0^\infty \frac{\varepsilon(t) t dt}{\sqrt{f(t)}(t^2 - \eta^2)}. \tag{4.20}$$



Figure 3: Parametrically defined function $l(\eta)$, $0 \le \eta < +\infty$, in cases (ii, section 3): a, b and (iii): c, d, when $k_0 = 1 + 0.1i$, $\beta = \pi/4$. Case a: $\kappa_0 = 0$ ($\gamma_1^+ = 1.5 + 0.5i$, $\gamma_4^+ = 1 + i$, $\gamma_1^- = 1 - 0.5i$, $\gamma_4^- = 1 + i$). Case b: $\kappa_0 = 1$ (the anticlockwise direction, $\gamma_1^+ = 1 + i$, $\gamma_4^+ = 1 - i$, $\gamma_1^- = 1 - i$, $\gamma_4^- = 1 + i$). Case c: $\kappa_0 = 0$ ($\gamma_1^+ = 1 + 3i$, $\gamma_4^+ = 1 + 4i$, $\gamma_1^- = 1 + i$, $\gamma_4^- = 1 + 2i$). Case d: $\kappa_0 = -1$ (the clockwise direction, $\gamma_1^+ = 1 + 0.5i$, $\gamma_4^+ = 1 + i$, $\gamma_1^- = 2 + 0.5i$, $\gamma_4^- = 1 + 2i$).

This integral is bounded as $\eta \to 0$ when $\kappa_0 = 0$ and has a logarithmic singularity otherwise,

$$\psi_0(\eta, w) = (-1)^{j-1}\kappa_0 \log \eta + O(1), \quad \eta \to 0, \quad (\eta, w) \in \mathbb{C}_j, \quad j = 1, 2. \tag{4.21}$$

It can be directly verified that the function

$$\hat{\psi}_0(\eta, w) = \psi_0(\eta, w) + \kappa_0 \sum_{j=1}^{2} (-1)^j \int_{q_{0j}}^{q_{1j}} \frac{w + \xi}{2\xi} \frac{dt}{t - \eta} \tag{4.22}$$

is bounded at the point $\eta = 0$. Here, q_{0j} are the two zero points of the surface, $q_{0j} = (0, (-1)^{j-1}\sqrt{f(0)})$, and $q_{1j} = ((-1)^{j-1}\rho_0, (-1)^{j-1}\sqrt{f(\rho_0)}) \in \mathbb{C}_j$, where ρ_0 is an arbitrary fixed point in the upper half-plane which coincides with none of the branch points a_j ($j = 1, 2, 3, 4$), the point η_0, and the roots of the polynomials $d_1(\eta)$ and $\delta_0(\eta)\delta_0(-\eta)$. Due to the symmetry of the points q_{11} and q_{12} we can rewrite the function $\hat{\psi}_0(\eta, w)$ as

$$\hat{\psi}_0(\eta, w) = \psi_0(\eta, w) + \kappa_0 \left[\int_0^{\rho_0} \frac{\eta dt}{t^2 - \eta^2} + w \int_0^{\rho_0} \frac{t dt}{\sqrt{f(t)}(t^2 - \eta^2)} \right]. \tag{4.23}$$

The function $\exp\{\hat{\psi}_0(\eta, w\}$ satisfies the boundary condition of the RHP (4.8). However, at the infinite points of the surface it has essential singularities due to the second order pole at infinity of the function (4.23). In order to remove this singularity, we cut the surface $\mathfrak{R}$ along the loops $\mathbf{a}_j$ and



Figure 4: The canonical cross-sections $\mathbf{a}_j$ and $\mathbf{b}_j$, $j = 1, 2, 3$.

$\mathbf{b}_j$ $(j = 1, 2, 3)$ which form a system of canonical cross-sections (Fig. 4). The loops $\mathbf{a}_j$ intersect the loops $\mathbf{b}_j$ at one point and do not intersect the other loops. The cross-sections $\mathbf{a}_1$ and $\mathbf{a}_2$ and $\mathbf{b}_1$ and $\mathbf{b}_2$ are symmetric with respect to the origin. The curves $\mathbf{a}_1$, $\mathbf{a}_2$ and $\mathbf{a}_3$ are closed contours which join the branch points $-a_1$ with $-a_2$, a_1 with a_2 and a_3 with a_4, respectively, and lie on both sheets of the surface. The loops $\mathbf{b}_1$, $\mathbf{b}_2$ and $\mathbf{b}_3$ join the points $-a_2$ with a_3, $-a_3$ with a_2 and $-a_4$ with a_4, respectively, and pass through the infinite points of the surface. The solid lines in Fig. 4 correspond to the parts of the loops on the sheet $\mathbb{C}_1$, while the broken lines show the parts of the loops on the second sheet. Because of the symmetry of the surface, to remove the essential singularity at infinity, it suffices to add to the function $\hat{\psi}(\eta, w)$ only the symmetric integrals,

$$\psi(\eta, w) = \hat{\psi}_0(\eta, w) + \left(\int_{p_0}^{p_1} + \int_{-p_0}^{-p_1} + m_0 \oint_{\mathbf{a}_1} + m_0 \oint_{\mathbf{a}_2} + n_0 \oint_{\mathbf{b}_1} + n_0 \oint_{\mathbf{b}_2} \right) \frac{w + \xi}{2\xi} \frac{dt}{t - \eta}. \tag{4.24}$$

Here, the point $p_0 = (\sigma_0, \sqrt{f(\sigma_0)})$ is an arbitrary fixed point in the sheet $\mathbb{C}_1$, while the point $p_1 = (\sigma_1, w(\sigma_1))$ may lie on either sheet of the surface and has to be determined. The numbers m_0 and n_0 are integers to be fixed. The contour $p_0 p_1$ is a smooth simple curve on the surface that does not cross the loops $\mathbf{a}_j$ and $\mathbf{b}_j$ $(j = 1, 2)$.

The function $\psi(\eta, w)$ admits a simple alteration

$$\psi(\eta, w) = \frac{w}{2\pi i} \int_0^\infty \frac{\varepsilon(t) t dt}{\sqrt{f(t)}(t^2 - \eta^2)} + \kappa_0 \int_0^{\rho_0} \left(\eta + \frac{wt}{\sqrt{f(t)}} \right) \frac{dt}{t^2 - \eta^2}$$
$$+ \left(\int_{p_0}^{p_1} + m_0 \oint_{\mathbf{a}_2} + n_0 \oint_{\mathbf{b}_2} \right) \frac{w + \xi}{\xi} \frac{t dt}{t^2 - \eta^2}. \tag{4.25}$$

The analysis of the solution at the infinite points of the surface shows that both functions, $\psi(\eta, w)$

and $\chi(\eta, w) = \exp\{\psi(\eta, w)\}$, are bounded as $\eta \to \infty$ if and only if the following condition holds

$$\frac{1}{2\pi i}\int_0^\infty \frac{\varepsilon(t)tdt}{\sqrt{f(t)}} + \kappa_0 \int_0^{\rho_0} \frac{tdt}{\sqrt{f(t)}} + \int_{p_0}^{p_1} \frac{tdt}{\xi} + m_0 \oint_{\mathbf{a}_2} \frac{tdt}{\xi} + n_0 \oint_{\mathbf{b}_2} \frac{tdt}{\xi} = 0. \tag{4.26}$$

4.3 Jacobi inversion problem

The condition (4.26) can be reduced to a genus-1 Jacobi inversion problem solvable by inversion of an elliptic integral. First, we express the integrals over the loops $\mathbf{a}_2$ and $\mathbf{b}_2$

$$\oint_{\mathbf{a}_2} \frac{tdt}{\xi} = \int_{a_1^2}^{a_2^2} \frac{dt}{\sqrt{f_*(t)}},$$

$$\oint_{\mathbf{b}_2} \frac{tdt}{\xi} = \int_{a_2^2}^{\infty} \frac{dt}{\sqrt{f_*(t)}} + \int_{\infty}^{a_3^2} \frac{dt}{\sqrt{f_*(t)}} \tag{4.27}$$

through elliptic integrals. Here, $f(t) = f_*(t^2)$, and the branch $\sqrt{f_*(\eta_*)}$ is fixed by the condition $\sqrt{f_*(\eta_*)} \sim 2i\eta_*^2 \sin^4\beta$, $\eta_* \to \infty$, in the η_*-plane ($\eta_* = \eta^2$) cut along the two lines joining the branch points, a_1^2 with a_2^2 and a_3^2 with a_4^2. By making the homographic transformation **(19)** $t = (\alpha_1 + \alpha_2\tau)(1 - \mu\tau)^{-1}$ we fix the parameters α_1, α_2 and μ such that the points a_1^2, a_2^2, a_3^2, and a_4^2 are mapped into the points 1, $1/\kappa$, $-1/\kappa$ and -1, respectively (κ is to be determined). It directly follows that

$$\frac{t - a_4^2}{a_1^2 - a_4^2} = \frac{(1-\mu)(1+\tau)}{2(1-\mu\tau)}, \quad \frac{t - a_1^2}{a_4^2 - a_1^2} = \frac{(1+\mu)(1-\tau)}{2(1-\mu\tau)}, \tag{4.28}$$

and

$$\frac{t - a_3^2}{a_2^2 - a_3^2} = \frac{(1-\mu/\kappa)(1+\kappa\tau)}{2(1-\mu\tau)}, \quad \frac{t - a_2^2}{a_3^2 - a_2^2} = \frac{(1+\mu/\kappa)(1-\kappa\tau)}{2(1-\mu\tau)}. \tag{4.29}$$

Equations (4.28) imply

$$\frac{t - a_4^2}{t - a_1^2} = \frac{(\mu-1)(1+\tau)}{(\mu+1)(1-\tau)}. \tag{4.30}$$

On putting in this equation $t = a_2^2$, $\tau = 1/\kappa$ and $t = a_3^2$, $\tau = -1/\kappa$ and denoting $\mu_0 = (\mu-1)/(\mu+1)$, $\kappa_0 = (\kappa-1)/(\kappa+1)$ we obtain the system of equations

$$\frac{\mu_0}{\kappa_0} = \frac{a_2^2 - a_4^2}{a_2^2 - a_1^2}, \quad \mu_0\kappa_0 = \frac{a_3^2 - a_4^2}{a_3^2 - a_1^2}. \tag{4.31}$$

It has two sets of solutions

$$\mu_0 = \pm\sqrt{\frac{(a_2^2 - a_4^2)(a_3^2 - a_4^2)}{(a_2^2 - a_1^2)(a_3^2 - a_1^2)}}, \quad \kappa_0 = \pm\sqrt{\frac{(a_2^2 - a_1^2)(a_3^2 - a_4^2)}{(a_2^2 - a_4^2)(a_3^2 - a_1^2)}}. \tag{4.32}$$

Each of them defines the parameters μ and κ,

$$\mu = \frac{1+\mu_0}{1-\mu_0}, \quad \kappa = \frac{1+\kappa_0}{1-\kappa_0}. \tag{4.33}$$

By expressing t from the two relations (4.28) and adding the formulas obtained we have the homographic transformation sought

$$t = \frac{a_1^2 + a_4^2}{2} + \frac{(a_1^2 - a_4^2)(\tau - \mu)}{2(1-\mu\tau)}. \tag{4.34}$$

We next differentiate the two equations (4.29) and find

$$dt = \frac{\sqrt{(1-\mu^2)(\kappa-\mu^2/\kappa)(a_2^2-a_3^2)(a_1^2-a_4^2)}}{2(1-\mu\tau)^2}d\tau. \tag{4.35}$$

On multiplying the four relations in (4.28) and (4.29) and using (4.25) and (4.35) we deduce

$$\int \frac{dt}{\sqrt{f_*(t)}} = \epsilon h \int \frac{d\tau}{\sqrt{(1-\tau^2)(1-\kappa^2\tau^2)}}, \tag{4.36}$$

where

$$h = \frac{1}{i\sin^4\beta}\sqrt{\frac{\kappa}{(a_2^2-a_3^2)(a_1^2-a_4^2)}}, \tag{4.37}$$

ϵ is real, $|\epsilon| = 1$, and $v(\tau) = \sqrt{(1-\tau^2)(1-\kappa^2\tau^2)}$ is the branch of the two-valued function $v^2 = (1-\tau^2)(1-\kappa^2\tau^2)$ in the τ-plane cut along the segments $[-1/\kappa, -1]$ and $[1, 1/\kappa]$ which meets the condition $v(0) = 1$. We wish now to compute the integral over the loop $\mathbf{a}_2$ in (4.27). Since $v(\tau) = -i|v(\tau)|$ as $\tau \in [1, 1/\kappa]$, from (4.36),

$$\oint_{\mathbf{a}_2} \frac{tdt}{\xi} = \epsilon h \int_1^{1/\kappa} \frac{d\tau}{v(\tau)} = \epsilon h i \mathbf{K}', \tag{4.38}$$

where $\mathbf{K}' = \mathbf{K}(\sqrt{1-\kappa^2})$ and $\mathbf{K} = \mathbf{K}(\kappa)$ is the complete elliptic integral of the first kind. To fix the sign of ϵ, it is sufficient to consider the case when all a_j^2 are real and $a_1^2 < a_2^2 < a_3^2 < a_4^2$. The branch $\sqrt{f_*(\eta_*)}$ has been fixed by the condition $\sqrt{f_*(\eta_*)} \sim 2i\eta_*^2 \sin^4\beta$, $\eta_* \to \infty$, and therefore $\sqrt{f_*(\eta_*)} = i|\sqrt{f_*(\eta_*)}|$ as $\eta_* \in [a_3^2, a_4^2]$. This implies $\epsilon = -1$.

To compute the integral over the loop $\mathbf{b}$ in (4.27), we note that $v(\tau) = -|v(\tau)|$ as $1/\kappa < \tau < +\infty$ and derive

$$\oint_{\mathbf{b}_2} \frac{tdt}{\xi} = -2h \int_{1/\kappa}^{\infty} \frac{d\tau}{v(\tau)} = 2h\mathbf{K}. \tag{4.39}$$

Denote next

$$\hat{\sigma}_j = \frac{\sigma_j^2 - a_+ + a_-\mu}{\mu\sigma_j^2 + a_- - a_+\mu}, \quad a_\pm = \frac{a_1^2 \pm a_4^2}{2}, \quad j = 1, 2. \tag{4.40}$$

On making the transformation (4.34) in the second integral in (4.26) we derive

$$\int_{p_0}^{p_1} \frac{tdt}{\xi} = -\frac{h}{2}\left(\int_{\hat{\sigma}_0}^{0} \frac{d\tau}{v(\tau)} + \int_0^{\hat{\sigma}_1} \frac{d\tau}{v(\tau)}\right) \tag{4.41}$$

in the case $p_1 \in \mathbb{C}_1$ and

$$\int_{p_0}^{p_1} \frac{tdt}{\xi} = -\frac{h}{2}\left(\int_{\hat{\sigma}_0}^{-1} \frac{d\tau}{v(\tau)} - \int_{-1}^{0} \frac{d\tau}{v(\tau)} - \int_0^{\hat{\sigma}_1} \frac{d\tau}{v(\tau)}\right) \tag{4.42}$$

in the case $p_1 \in \mathbb{C}_2$. Now the Jacobi inversion problem (4.26) may be put in a more convenient form. Let first $p_1 \in \mathbb{C}_1$. Then

$$\int_0^{\hat{\sigma}_1} \frac{d\tau}{v(\tau)} = \hat{d} + 4n_0\mathbf{K} - 2im_0\mathbf{K}', \tag{4.43}$$

where

$$\hat{d} = \frac{1}{\pi i h}\int_0^{\infty} \frac{\varepsilon(t)tdt}{\sqrt{f(t)}} + \frac{2\kappa_0}{h}\int_0^{\rho_0} \frac{tdt}{\sqrt{f(t)}} + \int_0^{\hat{\sigma}_0} \frac{d\tau}{v(\tau)}. \tag{4.44}$$

By inversion of the elliptic integral in (4.43) we find $\hat{\sigma}_1 = \operatorname{sn} \hat{d}$ and therefore the affix σ_1 of the point p_1 is given by

$$\sigma_1 = \pm\sqrt{a_+ + \frac{a_-(\hat{\sigma}_1 - \mu)}{1 - \mu\hat{\sigma}_1}}. \tag{4.45}$$

Because of the symmetry, either sign leads to the same solution. The integers m_0 and n_0 can be directly found from (4.43)

$$m_0 = -\frac{\operatorname{Im}[(I_* - \hat{d})\overline{\mathbf{K}}]}{2\operatorname{Re}[\mathbf{K}\overline{\mathbf{K}'}]}, \quad n_0 = \frac{\operatorname{Re}[(I_* - \hat{d})\overline{\mathbf{K}'}]}{4\operatorname{Re}[\mathbf{K}\overline{\mathbf{K}'}]}, \tag{4.46}$$

where I_* is an elliptic integral of the first kind

$$I_* = \int_0^{\hat{\sigma}_1} \frac{d\tau}{v(\tau)} = F(\sin^{-1}(\operatorname{sn} \hat{d}), \kappa). \tag{4.47}$$

If at least one of the numbers m_0, n_0 is not integer, then $p_1 \in \mathbb{C}_2$, and n_0, m_0 are both necessarily integer. In this case the Jacobi inversion problem (4.26) become

$$-\int_0^{\hat{\sigma}_1} \frac{d\tau}{v(\tau)} = \hat{d} + 4\left(n_0 + \frac{1}{2}\right)\mathbf{K} - 2im_0\mathbf{K}'. \tag{4.48}$$

The affix of the point p_1 is the same as in the previous case, while the integers m_0 and n_0 are different,

$$m_0 = \frac{\operatorname{Im}[(I_* + \hat{d})\overline{\mathbf{K}}]}{2\operatorname{Re}[\mathbf{K}\overline{\mathbf{K}'}]}, \quad n_0 = -\frac{1}{2} - \frac{\operatorname{Re}[(I_* + \hat{d})\overline{\mathbf{K}'}]}{4\operatorname{Re}[\mathbf{K}\overline{\mathbf{K}'}]}. \tag{4.49}$$

This completes the solution of the Jacobi problem.

5 Solution to the vector RHP

5.1 Matrix factorization and its analysis

As a matter of utility, it will be desirable to have the solution to the RHP (4.8) on the Riemann surface $\mathfrak{R}$ expressed in terms of two functions defined on the η-plane

$$\chi(\eta, w) = \exp\{\psi_1(\eta) + w\psi_2(\eta)\}, \tag{5.1}$$

where

$$\begin{aligned}
\psi_1(\eta) &= \frac{\kappa_0}{2}\log\frac{\eta - \rho_0}{\eta + \rho_0} + \frac{1}{2}\log\frac{\eta^2 - \sigma_1^2}{\eta^2 - \sigma_0^2}, \\
\psi_2(\eta) &= \frac{1}{2\pi i}\int_0^\infty \frac{\varepsilon(t)tdt}{\sqrt{f(t)}(t^2 - \eta^2)} + \kappa_0\int_0^{\rho_0} \frac{tdt}{\sqrt{f(t)}(t^2 - \eta^2)} \\
&\quad + \left(\int_{p_0}^{p_1} + m_0\oint_{\mathbf{a}_2} + n_0\oint_{\mathbf{b}_2}\right)\frac{tdt}{\xi(t^2 - \eta^2)},
\end{aligned} \tag{5.2}$$

Because the solution to the Jacobi problem, the point σ_1 and the integers m_0 and n_0, satisfy the condition (4.26), it is possible to alter formula (5.2) for the function $\psi_2(\eta)$ as

$$\psi_2(\eta) = \frac{1}{\eta^2}\left\{\frac{1}{2\pi i}\int_0^\infty \frac{\varepsilon(t)t^3dt}{\sqrt{f(t)}(t^2 - \eta^2)} + \kappa_0\int_0^{\rho_0} \frac{t^3dt}{\sqrt{f(t)}(t^2 - \eta^2)}\right.$$

$$+\left(\int_{p_0}^{p_1} + m_0\oint_{\mathbf{a}} + n_0\oint_{\mathbf{b}}\right)\frac{t^3dt}{\xi(t^2-\eta^2)}\Bigg\} \tag{5.3}$$

which can conveniently be used for large η. The analysis of this formula shows that the function $\psi_2(\eta)$ is bounded as $\eta\to\infty$, and therefore the essential singularity of the solution $\chi(\eta,w)$ has been removed.

With the solution to the RHP (4.25) on the surface $\mathfrak{R}$ at hand, we may write down formulas (4.9) for the factor-matrices $X^\pm(\eta)$ and their inverses in terms of functions defined on the η-plane

$$X^\pm(\eta)=e^{\psi_1^\pm(\eta)}\left[\cosh(f^{1/2}(\eta)\psi_2^\pm(\eta))I+\frac{1}{f^{1/2}(\eta)}\sinh(f^{1/2}(\eta)\psi_2^\pm(\eta))Q(\eta)\right],$$

$$[X^\pm(\eta)]^{-1}=e^{-\psi_1^\pm(\eta)}\left[\cosh(f^{1/2}(\eta)\psi_2^\pm(\eta))I-\frac{1}{f^{1/2}(\eta)}\sinh(f^{1/2}(\eta)\psi_2^\pm(\eta))Q(\eta)\right],\quad \eta\in\mathbb{C}^\pm. \tag{5.4}$$

It is essential for the solution of the vector RHP to study the behavior of the matrix $X(\eta)=X^\pm(\eta)$, $\eta\in\mathbb{C}^\pm$, at the points $p_0=(\sigma_0,\sqrt{f(\sigma_0)})\in\mathbb{C}_1$ and $p_1=(\sigma_1,w(\sigma_1))\in\mathfrak{R}$. For this purpose we use the representation (4.9). From (5.1), (5.2),

$$\chi(\eta,w)\sim\frac{E_{01}^\pm}{\eta\mp\sigma_0},\quad \eta\to\pm\sigma_0,\quad (\eta,w)\in\mathbb{C}_1,$$

$$\chi(\eta,-w)\sim E_{02}^\pm,\quad \eta\to\pm\sigma_0,\quad (\eta,-w)\in\mathbb{C}_2, \tag{5.5}$$

where $E_{0j}^\pm$ are nonzero constants. This yields

$$X(\eta)\sim\frac{E_\pm}{\eta\mp\sigma_0}Y^\pm,\quad \eta\to\pm\sigma_0, \tag{5.6}$$

where $Y^\pm=Y(\pm\sigma_0,\sqrt{f(\pm\sigma_0)})$ is a rank-1 2×2 matrix and $E_\pm$ are nonzero constants.

If p_1 is a point of the first sheet of the surface $\mathfrak{R}$, then

$$\chi(\eta,w)\sim E_{11}^\pm(\eta\mp\sigma_1),\quad \chi(\eta,-w)\sim E_{12}^\pm,\quad \eta\to\pm\sigma_1,\quad (\eta,(-1)^{j-1}w)\in\mathbb{C}_j,\quad j=1,2. \tag{5.7}$$

In the case $p_1\in\mathbb{C}_2$,

$$\chi(\eta,w)\sim E_{21}^\pm,\quad \chi(\eta,-w)\sim E_{22}^\pm(\eta\mp\sigma_1),\quad \eta\to\pm\sigma_1,\quad (\eta,(-1)^{j-1}w)\in\mathbb{C}_j,\quad j=1,2. \tag{5.8}$$

Here, $E_{sj}^\pm$ $(s,j=1,2)$ are nonzero constants. Then, regardless of whether the point p_1 belongs to the first sheet or the second one, the inverse matrix $[X(\eta)]^{-1}$ has a pole at the points $\pm\sigma_1$. Assume now that $\Psi(\eta)$ is an order-2 vector whose components have certain nonzero limits at the points $\eta=\pm\sigma_1$. Then since $Y(\eta,w)$ is a rank-1 matrix, we have

$$[X(\eta)]^{-1}\Psi(\eta)\sim\frac{E_j^\pm}{\eta\mp\sigma_1}\begin{pmatrix}1\\ s_j^\pm\end{pmatrix},\quad \eta\to\pm\sigma_1,\quad p_1\in\mathbb{C}_j,\quad j=1,2, \tag{5.9}$$

where $E_j^\pm$ =const, $s_j^\pm=n(\pm\sigma_1)[l(\pm\sigma_1)+w_j^\pm]^{-1}$, and $w_j^\pm=(-1)^{j-1}\sqrt{f(\pm\sigma_1)}$, for $p_1\in\mathbb{C}_j$, $j=1,2$. At the same time, if $\hat{\Psi}(\eta)$ is an order-2 vector such that

$$\hat{\Psi}(\eta)\sim\frac{\hat{E}_j^\pm}{\eta\mp\sigma_1}\begin{pmatrix}1\\ s_j^\pm\end{pmatrix},\quad \eta\to\pm\sigma_1, \tag{5.10}$$

where $\hat{E}_j^\pm$ are nonzero constants, then

$$X(\eta)\hat{\Psi}(\eta)=Y(\pm\sigma_1,-w_j^\pm)\frac{\hat{E}_j^\pm}{\eta\mp\sigma_1}\begin{pmatrix}1\\ s_j^\pm\end{pmatrix}+\tilde{\Psi}(\eta)=\tilde{\Psi}(\eta),\quad \eta\to\pm\sigma_1, \tag{5.11}$$

where $\tilde{\Psi}(\eta)$ is an order-2 vector bounded as $\eta\to\pm\sigma_1$.

We next examine the matrix $X(\eta)$ and its inverse as $\eta\to\pm\rho_0$. If $\kappa_0=0$, then both functions, $\psi_1(\eta)$ and $\psi_2(\eta)$, are bounded at the points $\pm\rho_0$, and therefore the matrices $X(\eta)$ and $[X(\eta)]^{-1}$ are bounded as well. If $|\kappa_0|=1$, then

$$\chi(\eta,w)\sim D_1^+(\eta-\rho_0)^{\kappa_0},\quad \eta\to\rho_0,\quad (\eta,w)\in\mathbb{C}_1,$$
$$\chi(\eta,w)\sim D_2^+,\quad \eta\to\rho_0,\quad (\eta,w)\in\mathbb{C}_2. \tag{5.12}$$

At the points with affix $-\rho_0$,

$$\chi(\eta,w)\sim D_1^-,\quad \eta\to-\rho_0,\quad (\eta,w)\in\mathbb{C}_1,$$
$$\chi(\eta,w)\sim D_2^-(\eta+\rho_0)^{-\kappa_0},\quad \eta\to-\rho_0,\quad (\eta,w)\in\mathbb{C}_2. \tag{5.13}$$

Here, $D_j^\pm$ are nonzero constants. At the points $\eta=\pm\kappa_0\rho_0$, the matrix $X(\eta)$ and its inverse accordingly behave

$$X(\eta)=O(1),\quad [X(\eta)]^{-1}\sim(\eta-\kappa_0\rho_0)^{-1}Y^{(0)}(\eta),\quad \eta\to\kappa_0\rho_0,$$
$$X(\eta)\sim(\eta+\kappa_0\rho_0)^{-1}Y^{(1)}(\eta),\quad [X(\eta)]^{-1}=O(1),\quad \eta\to-\kappa_0\rho_0, \tag{5.14}$$

where $Y^{(0)}(\kappa_0\rho_0)$ and $Y^{(1)}(-\kappa_0\rho_0)$ are rank-1 matrices.

Before proceeding with the solution of the vector RHP, we need to factorize the index-0 even function $\sqrt{\Delta(\eta)}$. It is given by

$$\sqrt{\Delta(\eta)}=\frac{\rho^+(\eta)}{\rho^-(\eta)},\quad \eta\in L, \tag{5.15}$$

where

$$\rho^\pm(\eta)=\exp\left\{\frac{1}{2\pi i}\int_L\frac{\log\sqrt{\Delta(t)}dt}{t-\eta}\right\}=\exp\left\{\frac{\eta}{2\pi i}\int_0^\infty\frac{\log\Delta(t)dt}{t^2-\eta^2}\right\},\quad \eta\in\mathbb{C}^\pm. \tag{5.16}$$

Referring now to the representations (3.20) and (4.7), we split the matrix $G(\eta)$ as

$$G(\eta)=\frac{\delta_*G^1(\eta)}{\delta_0(\eta)}\rho^+(\eta)X^+(\eta)[\rho^-(\eta)X^-(\eta)]^{-1},\quad \eta\in L. \tag{5.17}$$

We remind that $\delta_0(\eta)$ and $G^1(\eta)$ are the polynomial and polynomial matrix given by (3.14) and (3.17), respectively.

5.2 Vectors $\Phi^+(\eta)$ and $\Phi^-(\eta)$

To determine the vectors $\Phi^+(\eta)$ and $\Phi^-(\eta)$, we substitute the splitting (5.17) into the boundary condition (3.8) of the vector RHP and use the formulas

$$\hat{G}^1(\eta)=d_1(\eta)[G^1(\eta)]^{-1},\quad \hat{G}^1(\eta)=\begin{pmatrix}g_{22}^1(\eta) & -g_{12}^1(\eta)\\ -g_{21}^1(\eta) & g_{11}^1(\eta)\end{pmatrix}. \tag{5.18}$$

On factorizing the polynomial $d_1(\eta)$, we have

$$\frac{\delta_0(\eta)[X^+(\eta)]^{-1}\hat{G}^1(\eta)\Phi^+(\eta)}{\delta_*\alpha_2(\eta+t_1)(\eta+t_2))\rho^+(\eta)}=\frac{(\eta-t_1)(\eta-t_2)}{\rho^-(\eta)}[X^-(\eta)]^{-1}\Phi^-(\eta),\quad \eta\in L. \tag{5.19}$$

Here, $\pm t_1$ and $\pm t_2$ are the four zeros of the polynomial $d_1(\eta) = \alpha_2(\eta^2 - t_1^2)(\eta^2 - t_2^2)$, and $\operatorname{Im} t_j > 0$, $j = 1, 2$.

We begin with case (i) when the two zeros of the quadratic polynomial $\delta_0(\eta)$ lie in the lower half-plane, $\delta_0(\eta) = -(\eta+\tau_1)(\eta+\tau_2)\sin^2\beta$, $\operatorname{Im}\tau_j > 0$, $j = 1, 2$. On applying the principle of analytic continuation and the Liouville theorem, we have

$$\frac{\nu(\eta+\tau_1)(\eta+\tau_2)[X^+(\eta)]^{-1}\hat{G}^1(\eta)\Phi^+(\eta)}{(\eta+t_1)(\eta+t_2)\rho^+(\eta)} = \frac{(\eta-t_1)(\eta-t_2)}{\rho^-(\eta)}[X^-(\eta)]^{-1}\Phi^-(\eta) = R(\eta), \quad \eta \in \mathbb{C}, \tag{5.20}$$

where $\nu = -\delta_* \csc^2\beta$, and $R(\eta)$ is a rational vector-function. Note that due to (5.9) the vector $R(\eta)$ has simple poles at the points $\pm\sigma_1$. Also, because of (5.14) the vector $R(\eta)$ has simple poles at the points $\eta = \kappa_0\rho_0$ in the case $\kappa_0 = \pm 1$ and is bounded if $\kappa_0 = 0$. In addition, it has to have simple poles (the geometric optics poles) at the points $\eta = \pm\eta_0$. Since the vectors $\Phi^\pm(\eta)$ vanish, the matrices $[X^\pm(\eta)]^{-1}$ are bounded at infinity, and the elements of the matrix $G^1(\eta)$ are degree-2 polynomials, the vector $R(\eta)$ has a pole at the infinite point of multiplicity 1 if $\kappa_0 = 0$ and multiplicity 2 if $\kappa_0 = \pm 1$. The most general form of the vector $R(\eta)$ in the former case is given by

$$R(\eta) = \frac{P(\eta)}{(\eta^2 - \sigma_1^2)(\eta^2 - \eta_0^2)}, \tag{5.21}$$

where $P(\eta)$ is an order-2 vector whose components, $P_1(\eta)$ and $P_2(\eta)$, are degree-5 polynomials. In the case $\kappa_0 = \pm 1$,

$$R(\eta) = \frac{P(\eta)}{(\eta^2 - \sigma_1^2)(\eta^2 - \eta_0^2)(\eta - \kappa_0\rho_0)}, \tag{5.22}$$

where the components $P_1(\eta)$ and $P_2(\eta)$ of the vector $P(\eta)$ are degree-6 polynomials. The vectors $\Phi^\pm(\eta)$ can be deduced from (5.20)

$$\Phi^+(\eta) = \frac{\nu\rho^+(\eta)G^1(\eta)X^+(\eta)R(\eta)}{(\eta+\tau_1)(\eta+\tau_2)(\eta-t_1)(\eta-t_2)}, \quad \eta \in \mathbb{C}^+,$$

$$\Phi^-(\eta) = \frac{\rho^-(\eta)X^-(\eta)R(\eta)}{(\eta-t_1)(\eta-t_2)}, \quad \eta \in \mathbb{C}^-. \tag{5.23}$$

The solution has twelve arbitrary constants, the coefficients of the degree-5 polynomials $P_1(\eta)$ and $P_2(\eta)$ in the case $\kappa_0 = 0$ and fourteen constants if $\kappa_0 = \pm 1$.

In case (ii), when one of the zeros of the polynomial $\delta_0(\eta)$, τ_1, lies in the upper half-plane and the other, $\tau_2 \in \mathbb{C}_2$, $\delta_0(\eta) = -(\eta-\tau_1)(\eta+\tau_2)\sin^2\beta$, the boundary condition of the RHP gives

$$\frac{\nu(\eta+\tau_2)[X^+(\eta)]^{-1}\hat{G}^1(\eta)\Phi^+(\eta)}{(\eta+t_1)(\eta+t_2)\rho^+(\eta)} = \frac{(\eta-t_1)(\eta-t_2)}{(\eta-\tau_1)\rho^-(\eta)}[X^-(\eta)]^{-1}\Phi^-(\eta) = R(\eta), \quad \eta \in \mathbb{C}. \tag{5.24}$$

The rational vector $R(\eta)$ is given by (5.21), where $P_1(\eta)$ and $P_2(\eta)$ are polynomials of the fourth degree in the case $\eta_0 = 0$ and by (5.22) with the fifth degree polynomials in the case $\kappa_0 = \pm 1$. The rearrangement of the factors of the polynomial $\delta_0(\eta)$ produces the new solution

$$\Phi^+(\eta) = \frac{\nu\rho^+(\eta)G^1(\eta)X^+(\eta)R(\eta)}{(\eta+\tau_2)(\eta-t_1)(\eta-t_2)}, \quad \eta \in \mathbb{C}^+,$$

$$\Phi^-(\eta) = \frac{(\eta-\tau_1)\rho^-(\eta)X^-(\eta)R(\eta)}{(\eta-t_1)(\eta-t_2)}, \quad \eta \in \mathbb{C}^-, \tag{5.25}$$

which has either ten, or twelve arbitrary constants depending whether $\kappa_0 = 0$, or $\kappa_0 = \pm 1$.

In the third case, when both zeros of the polynomial $\delta_0(\eta)$ lie in the upper half-plane, $\delta_0(\eta) = -(\eta-\tau_1)(\eta-\tau_2)\sin^2\beta$, we have

$$\frac{\nu[X^+(\eta)]^{-1}\hat{G}^1(\eta)\Phi^+(\eta)}{(\eta+t_1)(\eta+t_2)\rho^+(\eta)} = \frac{(\eta-t_1)(\eta-t_2)}{(\eta-\tau_1)(\eta-\tau_2)\rho^-(\eta)}[X^-(\eta)]^{-1}\Phi^-(\eta) = R(\eta), \quad \eta \in \mathbb{C}. \tag{5.26}$$

As before, the rational vector $R(\eta)$ has the form (5.21) for $\kappa_0 = 0$ and (5.22) for $\kappa_0 = \pm 1$. However, the components of the vector $P(\eta)$ are degree-3 polynomials if $\kappa_0 = 0$ and degree-4 polynomials if $\kappa_0 = \pm 1$. The solution has eight arbitrary constants in the former case and ten constants in the second case. It may be written as

$$\Phi^+(\eta) = \frac{\nu\rho^+(\eta)G^1(\eta)X^+(\eta)R(\eta)}{(\eta-t_1)(\eta-t_2)}, \quad \eta \in \mathbb{C}^+,$$

$$\Phi^-(\eta) = \frac{(\eta-\tau_1)(\eta-\tau_2)\rho^-(\eta)X^-(\eta)R(\eta)}{(\eta-t_1)(\eta-t_2)}, \quad \eta \in \mathbb{C}^-. \tag{5.27}$$

5.3 Symmetry conditions

In general, the solution derived in the previous section does not meet the symmetry condition $\Phi^+(\eta) = \Phi^-(-\eta)$, $\eta \in \mathbb{C}$. We begin with case (i). In order to satisfy the symmetry condition, we rewrite it as

$$R(-\eta) = \frac{\nu(\eta+t_1)(\eta+t_2)[\rho^+(\eta)]^2}{(\eta+\tau_1)(\eta+\tau_2)(\eta-t_1)(\eta-t_2)}[X^-(-\eta)]^{-1}G^1(\eta)X^+(\eta)R(\eta), \quad \eta \in \mathbb{C}^+. \tag{5.28}$$

Here, we used the relation $\rho^+(\eta) = [\rho^-(-\eta)]^{-1}$, $\eta \in \mathbb{C}^+$. We wish now to simplify the matrix $U(\eta) = [X^-(-\eta)]^{-1}G^1(\eta)X^+(\eta)$. It will be convenient to represent the function $\psi_1(\eta)$ as the sum of the even and odd functions

$$\psi_1(\eta) = \psi_{1o}(\eta) + \psi_{1e}(\eta), \quad \psi_{1o}(\eta) = \frac{\kappa_0}{2}\log\frac{\eta-\rho_0}{\eta+\rho_0}, \quad \psi_{1e}(\eta) = \frac{1}{2}\log\frac{\eta^2-\sigma_1^2}{\eta^2-\sigma_0^2}, \tag{5.29}$$

(the function $\psi_{1o}(\eta) \equiv 0$ if $\kappa_0 = 0$) and use the following notations:

$$c = \cosh[\sqrt{f(\pm\eta)}\psi_2(\pm\eta)], \quad s = \sinh[\sqrt{f(\pm\eta)}\psi_2(\pm\eta)],$$

$$Q(\pm\eta) = \begin{pmatrix} l_\pm & m_\pm \\ n_\pm & -l_\pm \end{pmatrix}. \tag{5.30}$$

By referring now to (5.4), we transform the matrix $U(\eta)$ as

$$U(\eta) = e^{2\psi_{1o}(\eta)}\begin{pmatrix} c - sl_-/\sqrt{f} & -sm_-/\sqrt{f} \\ -sn_-/\sqrt{f} & c + sl_-/\sqrt{f} \end{pmatrix}\begin{pmatrix} g_{11}^1 & g_{12}^1 \\ g_{21}^1 & g_{22}^1 \end{pmatrix}\begin{pmatrix} c + sl_+/\sqrt{f} & sm_+/\sqrt{f} \\ sn_+/\sqrt{f} & c - sl_+/\sqrt{f} \end{pmatrix}. \tag{5.31}$$

On using next the directly verified identities

$$(l_+ - l_-)g_{11}^1 + n_+g_{12}^1 - m_-g_{21}^1 = 0, \quad m_+g_{11}^1 - (l_+ + l_-)g_{12}^1 - m_-g_{22}^1 = 0,$$

$$-n_-g_{11}^1 + (l_+ + l_-)g_{21}^1 + n_+g_{22}^1 = 0, \quad -n_-g_{12}^1 + m_+g_{21}^1 - (l_+ - l_-)g_{22}^1 = 0,$$

$$c^2g_{11}^1 + \frac{s^2}{f}(-l_-l_+g_{11}^1 - l_-n_+g_{12}^1 - l_+m_-g_{21}^1 - m_-n_+g_{22}^1) = g_{11}^1,$$

$$c^2g_{12}^1+\frac{s^2}{f}(-l_-m_+g_{11}^1+l_-l_+g_{12}^1-m_-m_+g_{21}^1+l_+m_-g_{22}^1)=g_{12}^1,$$

$$c^2g_{21}^1+\frac{s^2}{f}(-l_+n_-g_{11}^1-n_-n_+g_{12}^1+l_-l_+g_{21}^1+l_-n_+g_{22}^1)=g_{21}^1,$$

$$c^2g_{22}^1+\frac{s^2}{f}(-m_+n_-g_{11}^1+l_+n_-g_{12}^1+l_-m_+g_{21}^1-l_-l_+g_{22}^1)=g_{22}^1, \tag{5.32}$$

we ultimately deduce that $U(\eta)$ is a polynomial matrix and it coincides with $G^1(\eta)$ that is everywhere in the upper half- plane

$$[X^-(-\eta)]^{-1}G^1(\eta)X^+(\eta)=\left(\frac{\eta-\rho_0}{\eta+\rho_0}\right)^{\kappa_0}G^1(\eta). \tag{5.33}$$

We show next that $[\rho^+(\eta)]^2$ is a rational function. Consider the integral

$$\hat{\psi}(\eta)=\frac{\eta}{2\pi i}\int_0^\infty\frac{\log\Delta(t)dt}{t^2-\eta^2}, \tag{5.34}$$

where $\Delta(t)$ is defined in (3.25). On factorizing the function $\Delta(\eta)$ we obtain

$$\Delta(\eta)=\frac{(t^2-\tau_1^2)(t^2-\tau_2^2)}{(t^2-t_1^2)(t^2-t_2^2)}. \tag{5.35}$$

Hence we have to deal with the integral

$$\hat{\psi}(\eta)=\frac{\eta}{2\pi i}\int_0^\infty\log\frac{(t^2-\tau_1^2)(t^2-\tau_2^2)}{(t^2-t_1^2)(t^2-t_2^2)}\frac{dt}{t^2-\eta^2} \tag{5.36}$$

which can be evaluated explicitly

$$\hat{\psi}(\eta)=\pm\frac{1}{2}\log\frac{(\eta\pm\tau_1)(\eta\pm\tau_2)}{(\eta\pm t_1)(\eta\pm t_2)},\quad \eta\in\mathbb{C}^\pm. \tag{5.37}$$

Thus, we have proved that $[\rho^+(\eta)]^2$ is a rational function, and it has the form

$$[\rho^+(\eta)]^2=\frac{(\eta+\tau_1)(\eta+\tau_2)}{(\eta+t_1)(\eta+t_2)}. \tag{5.38}$$

For the present purpose, we transform the symmetry condition (5.28) as

$$R(-\eta)=\frac{\nu}{(\eta-t_1)(\eta-t_2)}\left(\frac{\eta-\rho_0}{\eta+\rho_0}\right)^{\kappa_0}G^1(\eta)R(\eta) \tag{5.39}$$

or, equivalently,

$$P(-\eta)=\frac{(-1)^{\kappa_0}\nu G^1(\eta)P(\eta)}{(\eta-t_1)(\eta-t_2)}, \tag{5.40}$$

where the components of the vector $P(\eta)$, $P_1(\eta)$ and $P_2(\eta)$, are polynomials

$$P_1(\eta)=\sum_{j=0}^{|\kappa_0|+5}a_j\eta^j,\quad P_2(\eta)=\sum_{j=0}^{|\kappa_0|+5}b_j\eta^j \tag{5.41}$$

whose coefficients are to be determined. On replacing η by $-\eta$ we reduce the condition (5.40) to

$$P(-\eta)=\frac{(\eta+t_1)(\eta+t_2)}{(-1)^{\kappa_0}\nu}[G^1(-\eta)]^{-1}P(\eta) \tag{5.42}$$

which is equivalent to the condition (5.40) since the matrix $G^1(\eta)$ possesses the following property:

$$G^1(\eta)G^1(-\eta) = d_1(\eta)I. \tag{5.43}$$

The symmetry condition (5.40) asserts that the coefficients of the polynomials $P_1(\eta)$ and $P_2(\eta)$ can be determined from the two equations

$$Q_1(\eta) = 0, \quad Q_2(\eta) = 0, \tag{5.44}$$

where

$$Q_j(\eta) = \sin^2\beta(\eta - t_1)(\eta - t_2)P_j(-\eta) + (-1)^{\kappa_0}\delta_*[g^1_{j1}(\eta)P_1(\eta) + g^1_{j2}(\eta)P_2(\eta)], \quad j = 1, 2, \tag{5.45}$$

are polynomials of degree $6 + |\kappa_0|$ (the terms $\eta^{7+|\kappa_0|}$ in both polynomials have zero-coefficients).

Consider first the case $\kappa_0 = 0$. To define the coefficients, we compute the derivatives $Q^{(m)}_j(\eta)$, $m = 0, 1, \ldots, 6; j = 1, 2$. The first six equations $Q^{(6-m)}_1(\eta) = 0$ $(m = 0, 1, \ldots, 5)$ express the coefficients b_{5-m} through the coefficients of the polynomial $P_1(\eta)$

$$b_{2j} = \nu_0(-a_{2j}\nu_1^- + a_{2j+1}\nu_2^+),$$
$$b_{2j+1} = \nu_0(-2a_{2j}\sin^2\beta - a_{2j+1}\nu_1^+ + a_{2j+2}\nu_2^-), \quad j = 0, 1, 2, \tag{5.46}$$

where

$$\nu_0 = \frac{\gamma_1^+ + \gamma_4^+}{2\cos\beta[(\gamma_4^+)^2 - \gamma_1^-\gamma_4^- + k^2\sin^2\beta]}, \quad \nu_1^\pm = \gamma_1^- - \gamma_4^- \pm (t_1 + t_2)\sin^2\beta,$$
$$\nu_2^\pm = \gamma_1^-\gamma_4^- + k^2\cos^2\beta \pm t_1t_2\sin^2\beta, \quad a_6 = 0. \tag{5.47}$$

The equation $Q_1(\eta) = 0$ yields

$$a_0[2\gamma_1^-\gamma_4^- + k^2\cos^2\beta - t_1t_2\sin^2\beta] = 0. \tag{5.48}$$

It is directly verified that $2\gamma_1^-\gamma_4^- + k^2\cos^2\beta - t_1t_2\sin^2\beta = 0$ and therefore a_0 is free. The other seven equations $Q^{(j)}_2 = 0$ $(j = 0, 1, \ldots, 6)$ are also identically satisfied provided the coefficients b_j $(j = 0, 1, \ldots, 5)$ are chosen as in (5.46), and t_1, t_2 are the two zeros in the upper-half plane of the even degree-4 polynomial $d_1(\eta)$.

A similar result holds for the case $|\kappa_0| = 1$. The equations $Q^{(7-m)}_1(\eta) = 0$ $(m = 0, 1, \ldots, 6)$ express the coefficients b_{6-m} through the coefficients of the polynomial $P_1(\eta)$

$$b_{2j} = \nu_0(-2a_{2j-1}\sin^2\beta - a_{2j}\nu_1^+ + a_{2j+1}\nu_2^-), \quad j = 0, 1, 2, 3, \quad a_{-1} = a_7 = 0,$$
$$b_{2j+1} = \nu_0(-a_{2j+1}\nu_1^- + a_{2j+2}\nu_2^+), \quad j = 0, 1, 2. \tag{5.49}$$

In the case $\kappa_0 = \pm 1$, we have $2\gamma_1^-\gamma_4^- + k^2\cos^2\beta + t_1t_2\sin^2\beta = 0$. Therefore, the equation $Q_1(\eta) = 0$, which is equivalent to

$$a_0[2\gamma_1^-\gamma_4^- + k^2\cos^2\beta + t_1t_2\sin^2\beta] = 0, \tag{5.50}$$

is satisfied for any a_0. If the coefficients b_j are defined by (5.49), then $Q_2(\eta) \equiv 0$.

Consequently, in case (i), the solution to the vector RHP possesses $6 + |\kappa_0|$ arbitrary constants a_j $(j = 0, 1, \ldots, 5 + |\kappa_0|)$ and satisfies the symmetry condition $\Phi^+(\eta) = \Phi^-(-\eta)$.

Consider next case (ii) when the two zeros of the polynomial $\delta_0(\eta)$ lie in the opposite half-planes. Since the relation (5.33) is invariant with respect to the location of the zeros of the polynomial $\delta_0(\eta)$, we employ it again and deduce from (5.25)

$$R(-\eta) = -\frac{\nu}{(\eta - t_1)(\eta - t_2)}\left(\frac{\eta - \rho_0}{\eta + \rho_0}\right)^{\kappa_0} G^1(\eta)R(\eta). \tag{5.51}$$

The rational vector $R(\eta)$ is given by (5.21) if $\kappa_0 = 0$ and by (5.22) if $\kappa_0 = \pm 1$, and

$$P_1(\eta) = \sum_{j=0}^{|\kappa_0|+4} a_j \eta^j, \quad P_2(\eta) = \sum_{j=0}^{|\kappa_0|+4} b_j \eta^j. \tag{5.52}$$

The symmetry condition (3.89.3) reads for the polynomials $P_1(\eta)$ and $P_2(\eta)$

$$P(-\eta) = \frac{(-1)^{\kappa_0+1}\nu G^1(\eta)P(\eta)}{(\eta - t_1)(\eta - t_2)}. \tag{5.53}$$

On following the procedure described for case (i) we obtain for $\kappa_0 = 0$

$$b_{2j} = \nu_0(-2a_{2j-1}\sin^2\beta - a_{2j}\nu_1^+ + a_{2j+1}\nu_2^-), \quad j = 0, 1, 2, \quad a_{-1} = a_5 = 0,$$

$$b_{2j+1} = \nu_0(-a_{2j+1}\nu_1^- + a_{2j+2}\nu_2^+), \quad j = 0, 1. \tag{5.54}$$

If $|\kappa_0| = 1$, then the coefficients b_{2j} and b_{2j+1} coincide with the corresponding coefficients in case (i), $\kappa = 0$, and are defined by (5.46). In case (ii), the solution is given by (5.25), (5.21), (5.22), (5.52), (5.54) and (5.46). It satisfies the symmetry conditions and possesses $5 + |\kappa_0|$ arbitrary constants $a_0, a_1, \ldots, a_{4+|\kappa_0|}$.

Finally, in case (iii), when the two zeros of the polynomial $\delta_0(\eta)$ lie in the upper half-plane, the symmetry relation coincides with the one derived in case (i) and is given by (5.39). The polynomials $P_1(\eta)$ and $P_2(\eta)$ in the representation of the solution (5.20) have the form

$$P_1(\eta) = \sum_{j=0}^{|\kappa_0|+3} a_j \eta^j, \quad P_2(\eta) = \sum_{j=0}^{|\kappa_0|+3} b_j \eta^j, \tag{5.55}$$

where the constants a_j $(j = 0, 1, \ldots, 3 + |\kappa_0|)$ are free and if $\kappa_0 = 0$,

$$b_{2j} = \nu_0(-a_{2j}\nu_1^- + a_{2j+1}\nu_2^+),$$

$$b_{2j+1} = \nu_0(-2a_{2j}\sin^2\beta - a_{2j+1}\nu_1^+ + a_{2j+2}\nu_2^-), \quad j = 0, 1, \quad a_4 = 0. \tag{5.56}$$

If $|\kappa_0| = 1$, the coefficients are defined by (5.54). The solution derived has $4 + |\kappa_0|$ arbitrary constants $a_0, a_1, \ldots, a_{3+|\kappa_0|}$.

5.4 Additional conditions

Since the vector polynomial $P(\eta)$ meets the condition (5.40) in the cases (i) and (iii) and the condition (5.53) in the case (ii) for all η, and the left-hand side in (5.40) and (5.53) is bounded at the points t_1 and t_2, due to (5.23), (5.25) and (5.27) the vector $\Phi^+(\eta)$, regardless of which case is considered, (i), (ii), or (iii), has removable singularities at the points t_1 and t_2 ($\operatorname{Im} t_j > 0$).

Now, the property (5.9) of the matrix $[X(\eta)]^{-1}$ asserts that at the point σ_1 the polynomials $P_1(\eta)$ and $P_2(\eta)$ satisfy the relation

$$s_1^+ P_1(\sigma_1) = P_2(\sigma_1). \tag{5.57}$$

Because of the symmetry condition this relation is necessary and sufficient for the removal of the simple pole of the solution at the points $\pm\sigma_1$.

According to the property (5.6) the solution to the vector RHP has simple poles at the points $\pm\sigma_0$. Since σ_0 is the affix of an arbitrary fixed point p_0 on the first sheet of the surface $\mathfrak{R}$ we may assume that $\operatorname{Im}\sigma_0 > 0$. Since Y^+ in (5.6) is a rank-1 matrix, by the symmetry property of the solution, the points $\pm\sigma_0$ are removable points of the vectors $\Phi^\pm(\eta)$ if and only if the following condition holds

$$Y_{11}^+ P_1(\sigma_0) + Y_{12}^+ P_2(\sigma_0) = 0, \tag{5.58}$$

where (Y_{11}^+, Y_{12}^+) is the first row of the matrix $Y(\sigma_0, \sqrt{f(\sigma_0)})$.

The solution derived has geometric optics poles at the points $\pm\eta_0$ ($\eta_0 = k \sin\theta_0 \sin\beta$) with the residues of the vector $\Phi^+(\eta)$ given by (3.7). This yields two extra equations for the determination of the six coefficients a_j. They are

$$\Xi S_1 = iE_0, \quad \Xi S_2 = iZH_0, \tag{5.59}$$

where

$$\Xi = \frac{\nu\rho^+(\eta_0)}{2\eta_0(\eta_0^2 - \sigma_1^2)(\eta_0 + \tau_1)^{\alpha_1}(\eta_0 + \tau_2)^{\alpha_2}(\eta_0 - t_1)(\eta_0 - t_2)},$$

$$S_j = [g_{j1}^1(\eta_0)X_{11}(\eta_0) + g_{j2}^1(\eta_0)X_{21}(\eta_0)]P_1(\eta_0) + [g_{j1}^1(\eta_0)X_{12}(\eta_0) + g_{j2}^1(\eta_0)X_{22}(\eta_0)]P_2(\eta_0), \tag{5.60}$$

where $X(\eta) = (X_{mn}(\eta))$, $m, n = 1, 2$, and $\alpha_1 = \alpha_2 = 1$ in case (i), $\alpha_1 = 0$, $\alpha_2 = 1$ in case (ii), and $\alpha_1 = \alpha_2 = 0$ in case (iii).

Let $\kappa_0 = 0$. There are s arbitrary constants $a_0, a_1, \ldots, a_{s-1}$, where s is equal to 6, 5 and 4 in the cases (i), (ii) and (iii), respectively. At the same time, there are four additional conditions regardless of which case is considered. Thus, the solution has two arbitrary constants in case (i), one constant in case (ii) and it is unique in case(iii).

When $\kappa_0 = 1$, according to (5.14) and (5.22), the vector $\Phi^+(\eta)$ has inadmissible pole at the point $\eta = \rho_0 \in \mathbb{C}^+$ (the point ρ_0 was chosen to be in the upper half-plane) due to the pole of the vector $R(\eta)$. The vector $\Phi^-(\eta)$ on the other hand has a simple pole at the point $\eta = -\rho_0$. Since Y_- in (5.14) is a rank-1 matrix, for the point $\eta = -\rho_0 \in \mathbb{C}^-$ being a removable point of $\Phi^-(\eta)$ it is necessary and sufficient that the following condition holds:

$$\tilde{Y}_{11} P_1(-\rho_0) + \tilde{Y}_{12} P_2(-\rho_0) = 0, \tag{5.61}$$

where $\tilde{Y}_{11}$ and $\tilde{Y}_{12}$ are the elements of the first row of the matrix $Y^{(1)}(-\rho_0)$. If the condition (5.61) is satisfied, because of the symmetry condition $\Phi^+(\eta) = \Phi^-(-\eta)$, the point $\eta = \rho_0 \in \mathbb{C}^+$ is a removable point of the vector $\Phi^+(\eta)$.

In the case $\kappa_0 = -1$, the matrix $X(\eta)$ has a simple pole at the point $\eta = \rho_0$, and the vector $R(\eta)$ has a simple pole at $\eta = -\rho_0$. Therefore, the solution $\Phi^\pm(\eta)$ has simple poles at the points $\pm\rho_0$. Similarly, to the previous case, it can be removed by the condition

$$\hat{Y}_{11} P_1(\rho_0) + \hat{Y}_{12} P_2(\rho_0) = 0, \tag{5.62}$$

where $\hat{Y}_{11}$ and $\hat{Y}_{12}$ are the elements of the first row of the matrix $Y^{(1)}(\rho_0)$.

Because in the case $|\kappa_0| = 1$ we have $s + 1$ free constants, $a_0, a_1, \ldots, a_s$, the number of free constants exceeds the number of additional conditions (it is five) by two in case (i) and by one in case (ii). In case (iii), the number of free constants and additional conditions is the same.

This completes the solution procedure for the RHP 1. Since the structure of the matrix coefficient $\tilde{G}(\eta)$ for the RHP 2 is the same as in the RHP 1 (the five parameters of the problem, $\gamma_1^\pm$, $\gamma_4^\pm$ and β, need to be changed according to the transformation (2.19)), the same method is applied to the RHP 2. As in the case of the RHP 1, the solvability of the RHP 2 is governed by the polynomial $\delta_0(\eta)$ which now becomes

$$\tilde{\delta}_0(\eta) = (\eta^2 - k_0^2)\cos^2\beta - (\eta - \gamma_1^+)(\eta - \gamma_4^+). \tag{5.63}$$

To summarize the result proved, we introduce a class of solutions. We say that $\phi_j(x,y)\in\mathcal{A}(W_e)$ if $\phi_j(x,y)\in C^2(W_e)\cap C^1(\overline{W_e})$ $(j=1,2)$ and

$$|\phi_1-E_z^i-E_z^r-E_z^s|\le K_1e^{-\varepsilon\rho},$$

$$|Z^{-1}\phi_2-H_z^i-H_z^r-H_z^s|\le K_2e^{-\varepsilon\rho},\quad 0\le\rho<\infty,\quad 0<\theta<\frac{\pi}{2},\tag{5.64}$$

where ε is a small positive number, K_1 and K_2 are finite positive constants, (E_z^i,H_z^i) is the incident wave (2.2), (E_z^r,H_z^r) is the reflected wave, and (E_z^s,H_z^s) is the surface wave.

Theorem 5.1. Let a right-angled concave wedge be illuminated by the incident wave (2.1) and the material properties of the wedge faces be described by the impedance boundary conditions (2.6). Let $\alpha=\pi/2$ *and* $\gamma_2^\pm=\gamma_3^\pm=0$. *Then, in the class of functions* $\mathcal{A}(W_e)$, *the boundary value problem (2.8), (2.9) has* $n+1$ *solutions, where* n *is the number of zeros in the lower half-plane of the characteristic degree-4 polynomial*

$$\delta_0(\eta)\tilde\delta_0(\eta)=[(\eta^2-k_0^2)\cos^2\beta-(\eta-\gamma_1^-)(\eta-\gamma_4^-)][(\eta^2-k_0^2)\cos^2\beta-(\eta-\gamma_1^+)(\eta-\gamma_4^+)],\tag{5.65}$$

where $k_0=k\sin\beta$ *and* $\operatorname{Im}k>0$. *In particular, the problem has a unique solution if and only if all the four zeros lie in the upper half-plane.*

5.5 Scalar case: $\beta=\pi/2$

As a test for the solvability results of Section 5.4, consider the scalar case when $\alpha=\beta=\pi/2$. The matrix coefficient $G(\eta)$ of the RHP 1 becomes the diagonal matrix

$$G(\eta)=\operatorname{diag}\{(\gamma_1^-+\eta)(\gamma_1^--\eta)^{-1},(\gamma_4^-+\eta)(\gamma_4^--\eta)^{-1}\},\tag{5.66}$$

and the vector RHP (3.8) reduces to the following two scalar RHPs:

Find two pairs of functions $\Phi_j^+(\eta)$ *and* $\Phi_j^-(\eta)$ *analytic in* $\mathbb{C}^+$ *and* $\mathbb{C}^-$, *respectively, except for the geometric optics poles* $\eta=\pm\eta_0$ *with residues defined by (3.7) and continuous up the real axis* L. *On the contour* L, *their limit values satisfy the boundary conditions*

$$\Phi_j^+(\eta)=\frac{\gamma_{j-}+\eta}{\gamma_{j-}-\eta}\Phi_j^-(\eta),\quad \eta\in L,\quad j=1,2,\tag{5.67}$$

where $\gamma_{1-}=\gamma_1^-$, $\gamma_{2-}=\gamma_4^-$. *At infinity,* $\Phi_j(\eta)=O(\eta^{-1})$, *and everywhere in the plane* $\Phi_j^+(\eta)=\Phi_j^-(-\eta)$.

The coefficients of the problems are rational functions, and the solution can easily be derived. The polynomial $\delta_0(\eta)$ introduced in (3.14) has the form $\delta_0(\eta)=-(\eta-\gamma_1^-)(\eta-\gamma_4^-)$. As before, we consider cases (i), (ii) and (iii). If both zeros of the polynomial $\delta_0(\eta)$ lie in the lower half-plane, that is if $\operatorname{Im}\gamma_{j-}<0$, $j=1,2$ (case i), then the solution to each RHP (5.67) has one arbitrary constant and has the form

$$\Phi_j^+(\eta)=\frac{C_{0j}+C_{1j}\eta^2}{(\eta^2-\eta_0^2)(\gamma_{j-}-\eta)},\quad \Phi_j^-(\eta)=\frac{C_{0j}+C_{1j}\eta^2}{(\eta^2-\eta_0^2)(\gamma_{j-}+\eta)},\quad j=1,2,\tag{5.68}$$

where

$$C_{01}=-C_{11}\eta_0^2+2iE_0\eta_0(\gamma_1^--\eta_0),\quad C_{02}=-C_{12}\eta_0^2+2iZH_0\eta_0(\gamma_4^--\eta_0),\tag{5.69}$$

and the constants C_{11} and C_{12} are free.

In case (iii), when both zeros of the polynomial lie in the upper half-plane, $\operatorname{Im}\gamma_{j-}>0$, $j=1,2$, the solution is unique and has the form

$$\Phi_j^+(\eta)=\frac{C_j(\gamma_{j-}+\eta)}{\eta^2-\eta_0^2},\quad \Phi_j^-(\eta)=\frac{C_j(\gamma_{j-}-\eta)}{\eta^2-\eta_0^2},\quad j=1,2,\tag{5.70}$$

where

$$C_1 = \frac{2i\eta_0 E_0}{\eta_0 + \gamma_1^-}, \quad C_2 = \frac{2i\eta_0 Z H_0}{\eta_0 + \gamma_4^-}. \tag{5.71}$$

Finally, in case (ii), when one of the zeros say, γ_1^- lies in the upper half-plane and the second one $\gamma_4^- \in \mathbb{C}^-$, the RHP for the electric field has the unique solution (5.70), (5.71) ($j = 1$), while the solution to the RHP for the magnetic field is given by (5.68), (5.69) ($j = 2$) and possesses one arbitrary constant. Thus, in each case the results for the test scalar problem are consistent with those obtained for the vector case in Section 5.4.

The RHP 2 reduces to the two scalar problems (5.67), where γ_{j-} needs to be replaced by γ_{j+}, and the solution is unique if and only if both $\operatorname{Im}\gamma_1^+$ and $\operatorname{Im}\gamma_4^+$ are positive. Otherwise, if $\operatorname{Im}\gamma_1^+ < 0$ and $\operatorname{Im}\gamma_4^+ < 0$, then the solution has two arbitrary constants, and if $\operatorname{Im}\gamma_1^+ \operatorname{Im}\gamma_1^+ < 0$, then there is one free constant.

Notice that this result is consistent with the uniqueness theorem proved in **(18)** for the scalar case ($\beta = \pi/2$) for a wedge $\mathcal{W} : |\theta| < \alpha$, $\alpha \in (0, \pi)$ by applying the Green theorem to the integral

$$\int_{\tilde{\mathcal{W}}} (\Delta + k^2 u)\overline{u} d\tilde{\mathcal{W}} \tag{5.72}$$

over a curvilinear rectangle $\tilde{\mathcal{W}} : \rho_0 < \rho < \rho_1, -\alpha < \theta < \alpha$ ($0 < \rho_0 < \rho_1 < \infty$). Here, u is the solution to the scalar impedance boundary value problem for the Helmholtz equation in the wedge $\mathcal{W}$.

6 Sommerfeld integral representation

In this section, we consider the case when all the four zeros of the characteristic polynomial $\delta_0(s)\tilde{\delta}_0(s)$ lie in the upper half-plane, and both RHPs have a unique solution. The electric and magnetic field can be given in terms of the Sommerfeld integrals as

$$\begin{pmatrix} E_z(\rho,\theta) \\ ZH_z(\rho,\theta) \end{pmatrix} = \frac{1}{2\pi i} \int_{\mathcal{T}} e^{-ik_0\rho\cos s} \begin{pmatrix} S_e(s+\theta) \\ S_h(s+\theta) \end{pmatrix} ds, \tag{6.1}$$

where $\mathcal{T}$ is the Sommerfeld double loop with the asymptotes $s = \pi/2$ and $s = -3\pi/2$ for the upper loop $\mathcal{T}_+$ lying in the upper half-plane. The starting point of the contour is chosen to be $s = \pi/2 + i\infty$. The second loop $\mathcal{T}_-$ is symmetric to $\mathcal{T}_+$ with respect to the origin.

6.1 Spectra $S_e(s)$ and $S_h(s)$

The purpose of this section is to derive expressions for the functions $S_e(s)$ and $S_h(s)$. The functions $S_e(s)$ and $S_h(s)$ are analytic everywhere in the strip $|\operatorname{Re} s| < \pi/2 + \epsilon$ ($\epsilon > 0$ and small) except for the simple poles $s = \pm\theta_0$, and

$$\operatorname*{res}_{s=\theta_0} S_e(s) = E_0, \quad \operatorname*{res}_{s=\theta_0} S_h(s) = ZH_0. \tag{6.2}$$

The knowledge of these functions enables us to determine the reflected, surface and diffracted fields. We begin with the function $S_e(s)$. On applying the inverse Maliuzhinets transform **(20)**,

$$S_e(\theta + s) - S_e(\theta - s) = ik_0 \sin s \int_0^\infty e^{ik_0\rho\cos s} E_z(\rho,\theta) d\rho, \tag{6.3}$$

and fixing first $\theta = 0$ and then $\theta = \pi/2$, we obtain the following two equations:

$$S_e(s) - S_e(-s) = ik_0 \sin s \int_0^\infty e^{ik_0 x\cos s} E_z(x, 0) dx,$$

$$S_e\left(\frac{\pi}{2}+s\right)-S_e\left(\frac{\pi}{2}-s\right)=ik_0\sin s\int_0^\infty e^{ik_0y\cos s}E_z(0,y)dy, \tag{6.4}$$

where the functions $E_z(x,0)$ and $E_z(0,y)$ are the sums of the associated functions generated by the waves E_z^{i+} (case 1) and E_z^{i-} (case 2). In the first case, the integrals in (6.4) with respect to x and y are the functions $\hat{\phi}_1(k_0\cos s,0)$ and $\tilde{\phi}_1(0,k_0\cos s)$, respectively, and can be expressed through the solution to the RHP 1, the functions $\Phi_1^\pm(\eta)$ and $\Phi_2^\pm(\eta)$. In the second case, these integrals are the functions $\tilde{\phi}_1(k_0\cos s,0)$ and $\hat{\phi}_1(0,k_0\cos s)$, respectively, and representable in terms of the solution to the RHP 2, the functions $\Psi_1^\pm(\eta)$ and $\Psi_2^\pm(\eta)$. On employing the first equation in (3.4) we determine $\hat{\phi}_1(k_0\cos s,0)$ in case 1 and and $\hat{\phi}_1(0,k_0\cos s)$ in case 2 (the parameters in (3.4) have to be transformed according to (2.19)). In both cases we take η as $k_0\sin s$ (because of the symmetry of the equation both solutions $\eta=\pm k_0\sin s$ of the equation $ik_0\cos s=-\sqrt{\eta^2-k_0^2}$ produce the same result). Equations (6.4) now have the form

$$S_e(s)-S_e(-s)=F_{1e}(s),\quad S_e\left(\frac{\pi}{2}+s\right)-S_e\left(\frac{\pi}{2}-s\right)=F_{2e}(s), \tag{6.5}$$

where

$$\begin{aligned}F_{1e}(s)&=ik_0\sin s\Psi_1^+(k_0\cos s)-\frac{i}{2}(\gamma_1^++k_0\cos s)[\Phi_1^+(k_0\sin s)-\Phi_1^-(k_0\sin s)]\\&\quad+\frac{i}{2}k_0\cos\beta\sin s[\Phi_2^+(k_0\sin s)+\Phi_2^-(k_0\sin s)],\\F_{2e}(s)&=ik_0\sin s\Phi_1^+(k_0\cos s)-\frac{i}{2}(\gamma_1^-+k_0\cos s)[\Psi_1^+(k_0\sin s)-\Psi_1^-(k_0\sin s)]\\&\quad-\frac{i}{2}k_0\cos\beta\sin s[\Psi_2^+(k_0\sin s)+\Psi_2^-(k_0\sin s)].\end{aligned} \tag{6.6}$$

We will adopt the Fourier transform in the form **(20)** and use the following notations for the transforms and their inverses:

$$\begin{aligned}\hat{S}_e(t)&=-\frac{1}{2\pi}\int_{-i\infty}^{i\infty}S_e(s)e^{ist}ds,\quad S_e(s)=\int_{-i\infty}^{i\infty}\hat{S}_e(t)e^{-ist}dt,\\\hat{F}_{je}(t)&=-\frac{1}{2\pi}\int_{-i\infty}^{i\infty}F_{je}(s)e^{ist}ds,\quad F_{je}(s)=\int_{-i\infty}^{i\infty}\hat{F}_{je}(t)e^{-ist}dt.\end{aligned} \tag{6.7}$$

When applied to the functions $S_e(\pi/2\pm s)$ this transformation yields

$$\begin{aligned}-\frac{1}{2\pi}\int_{-i\infty}^{i\infty}S_e\left(\frac{\pi}{2}\pm s\right)e^{ist}ds&=-\frac{e^{\mp i\pi t/2}}{2\pi}\int_{\pi/2-i\infty}^{\pi/2+i\infty}S_e(s)e^{\pm ist}ds\\&=\hat{S}_e(\pm t)e^{\mp i\pi t/2}-iE_0e^{\pm i(\theta_0-\pi/2)t}.\end{aligned} \tag{6.8}$$

Here, we used the fact that the function $S_e(s)$ is analytic everywhere in the strip $|\operatorname{Re}s|<\pi/2+\epsilon$ apart from a simple pole at the point $s=\theta_0$ with the residue given by (6.2). From these we find that corresponding to (6.5) we have the pair of equations

$$\begin{aligned}\hat{S}_e(t)-\hat{S}_e(-t)&=\hat{F}_{1e}(t),\\\hat{S}_e(t)e^{-i\pi t/2}-\hat{S}_e(-t)e^{i\pi t/2}&=\hat{F}_{2e}(t)+2E_0\sin\left(\frac{\pi}{2}-\theta_0\right)t.\end{aligned} \tag{6.9}$$

Because of the symmetry of these equations, it suffices to determine one of the functions $\hat{S}_e(t)$, $\hat{S}_e(-t)$

$$\hat{S}_e(t)=\frac{\hat{F}_{1e}(t)e^{i\pi t/2}-\hat{F}_{2e}(t)}{2i\sin\pi t/2}+\frac{iE_0\sin(\pi/2-\theta_0)t}{\sin\pi t/2}. \tag{6.10}$$

It only remains to apply the inverse transform (6.7) and use the integral

$$\int_{-i\infty}^{i\infty}\frac{e^{i\sigma t}dt}{\sin \pi t/2}=-2\tan\sigma,\quad -\frac{\pi}{2}<\operatorname{Re}\sigma<\frac{\pi}{2},\tag{6.11}$$

to obtain an integral representation for the function $S_e(s)$. We find

$$S_e(s)=S_e^{(1)}(s)+S_e^{(2)}(s)+E_0[\cot(s-\theta_0)-\cot(s+\theta_0)],\tag{6.12}$$

where

$$S_e^{(1)}(s)=-\frac{1}{2\pi i}\int_{-i\infty}^{i\infty}F_{1e}(\sigma)\cot(\sigma-s)d\sigma,\quad 0<\operatorname{Re}s<\pi,$$

$$S_e^{(2)}(s)=-\frac{1}{2\pi i}\int_{-i\infty}^{i\infty}F_{2e}(\sigma)\tan(\sigma-s)d\sigma,\quad -\frac{\pi}{2}<\operatorname{Re}s<\frac{\pi}{2}.\tag{6.13}$$

The function $S_e(s)$ is analytic everywhere in the strip $0<\operatorname{Re}s<\pi/2$ except for the point $s=\theta_0$, where it has a simple pole with the residue equal to E_0. In order to recover the reflected, surface and diffracted waves, we analytically continue the function $S_e(s)$ from the strip $0<\operatorname{Re}s<\pi/2$ to the right and to the left to the strips $\pi/2<\operatorname{Re}s<2\pi$ and $-3\pi/2<\operatorname{Re}s<0$. We have found that the solutions to the RHPs 1 and 2, the functions $\Phi_j^\pm(\eta)$ and $\Psi_j^\pm(\eta)$, have simple poles at the points $\pm\eta_0$ and $\pm\tilde\eta_0$, respectively. It will be convenient to represent them as

$$\Phi_j^\pm(\eta)=\frac{\hat\Phi_j^\pm(\eta)}{\eta^2-\eta_0^2},\quad \Psi_j^\pm(\eta)=\frac{\hat\Psi_j^\pm(\eta)}{\eta^2-\tilde\eta_0^2},\quad j=1,2,\tag{6.14}$$

where $\hat\Phi_j^\pm(\eta)$ and $\hat\Psi_j^\pm(\eta)$ are bounded and nonzero at the points $\pm\eta_0$ and $\pm\tilde\eta_0$, respectively. Starting with the function $S_e^{(2)}(s)$ given by (6.13) and analytic in the strip $-\pi/2<\operatorname{Re}s<\pi/2$ we continue it to the strip $\pi/2<\operatorname{Re}s<3\pi/2$ by shifting the contour $\operatorname{Im}s=0$ to the right by π. In the strip $0<\operatorname{Re}s<\pi$, the function $F_{2e}(s)$ has two geometric optics poles, $s=\pi/2-\theta_0$ and $s=\pi/2+\theta_0$. In addition, it may have some poles which generate surface waves. Indeed, when $0<\operatorname{Re}s<\pi$ and $\operatorname{Im}(k_0\cos s)<0$, the function $\Phi_1^+(k_0\cos s)$ needs to be continued analytically from the domain $0<\operatorname{Re}s<\pi$ and $\operatorname{Im}(k_0\cos s)>0$, where it is analytic (except for the geometric optics poles). The same is applied to the functions $\Psi_j^+(k_0\sin s)$ and $\Psi_j^-(k_0\sin s)$ $(j=1,2)$, when $\operatorname{Im}(k_0\sin s)<0$ and $\operatorname{Im}(k_0\sin s)>0$, respectively. From the RHPs 1 and 2 boundary conditions we derive

$$\Phi^+(\eta)=\frac{G^0(\eta)+\zeta(\eta)G^1(\eta)}{d(\eta)}\Phi^-(\eta),\quad \Psi^+(\eta)=\frac{\tilde G^0(\eta)+\zeta(\eta)\tilde G^1(\eta))}{\tilde d(\eta)}\Psi^-(\eta),\quad \eta\in\mathbb{C}^-,\tag{6.15}$$

where $\tilde G^0(\eta)$ and $\tilde G^1(\eta)$ are obtained from $G^0(\eta)$ and $G^1(\eta)$, respectively, by the transformation (2.19). Here, $\zeta(k_0\sin s)=-ik_0\cos s$ and $\zeta(k_0\cos s)=-ik_0\sin s$, and $G^j(\eta)$ and $\tilde G^j(\eta)$ are polynomial matrices. Notice that

$$d(k_0\cos s)=-d^+(k_0\sin s)d^-(-k_0\cos s),\quad d(k_0\sin s)=-d^+(k_0\cos s)d^-(-k_0\sin s),$$

$$\tilde d(k_0\cos s)=-d^-(k_0\sin s)d^+(-k_0\cos s),\quad \tilde d(k_0\sin s)=-d^-(k_0\cos s)d^+(-k_0\sin s),\tag{6.16}$$

where

$$d^\pm(t)=t^2\sin^2\beta+(\gamma_1^\pm+\gamma_4^\pm)t+\gamma_1^\pm\gamma_4^\pm+k_0^2\cos^2\beta.\tag{6.17}$$

Notice that $d^-(-t)$ and $d^+(-t)$ coincide with the polynomials $\delta_0(t)$ and $\tilde\delta_0(t)$ given by (3.14) and (5.63), respectively. Introduce next the numbers

$$t_1^\pm=\frac{-(\gamma_1^\pm+\gamma_4^\pm)+\sqrt{\delta_\pm}}{2k_0\sin^2\beta},\quad t_2^\pm=\frac{-(\gamma_1^\pm+\gamma_4^\pm)-\sqrt{\delta_\pm}}{2k_0\sin^2\beta},\tag{6.18}$$

where

$$\delta_\pm = (\gamma_1^\pm + \gamma_4^\pm)^2 - 4\sin^2\beta(\gamma_1^\pm\gamma_4^\pm + k_0^2\cos^2\beta). \tag{6.19}$$

In the case of the RHP 1, we need the zeros of the functions $d(k_0 \sin s)$ which are defined by the equations $\cos s = t_{1,2}^+$ and $\sin s = -t_{1,2}^-$ and given by

$$s = \pm i \log(t_{1,2}^+ \pm \sqrt{(t_{1,2}^+)^2 - 1}) + 2\pi k', \quad s = \pi/2 \mp [\pi/2 + i\log(-it_{1,2}^- + \sqrt{1-(t_{1,2}^-)^2})] + 2\pi k'', \tag{6.20}$$

Also, we require the zeros of the function $d(k_0 \cos s)$ which are

$$s = \pm i \log(-t_{1,2}^- \pm \sqrt{(t_{1,2}^-)^2 - 1}) + 2\pi m', \quad s = \pi/2 \mp [\pi/2 + i\log(it_{1,2}^+ + \sqrt{1-(t_{1,2}^+)^2})] + 2\pi m''. \tag{6.21}$$

Here, k', k'' m' and m'' are integers. When the RHP 2 solutions are analytically continued, we need to know the zeros of the functions $\tilde{d}(k_0 \sin s)$ and $\tilde{d}(k_0 \cos s)$. The zeros of the former function are given by

$$s = \pm i \log(t_{1,2}^- \pm \sqrt{(t_{1,2}^-)^2 - 1}) + 2\pi k', \quad s = \pi/2 \mp [\pi/2 + i\log(-it_{1,2}^+ + \sqrt{1-(t_{1,2}^+)^2})] + 2\pi k'', \tag{6.22}$$

while the zeros of the function $\tilde{d}(k_0 \cos s) = -d^+(-\cos s)d^-(\sin s)$ are

$$s = \pm i \log(-t_{1,2}^\pm \sqrt{(t_{1,2}^+)^2 - 1}) + 2\pi m', \quad s = \pi/2 \mp [\pi/2 + i\log(it_{1,2}^- + \sqrt{1-(t_{1,2}^-)^2})] + 2\pi m''. \tag{6.23}$$

Denote $s_{ej}^{(2R)}$ $(j = 1, \dots, n_2')$ the poles of the function $d(k_0 \cos s)$ lying in the domain $0 < \operatorname{Re} s < \pi$, $\operatorname{Im}(k_0 \cos s) < 0$ and the poles of the function $\tilde{d}(k_0 \sin s)$ in the strip $0 < \operatorname{Re} s < \pi$ (call these poles the surface wave poles). Let θ_j $(j = 1, \dots, 4)$ be the geometric optics poles in the strip $0 < \operatorname{Re} s < \pi$, the points $\pi/2 - \theta_0$ and $\pi/2 + \theta_0$. We can write

$$S_e^{(2)}(s) = -\frac{1}{2\pi i}\int_{\pi - i\infty}^{\pi + i\infty} F_{2e}(\sigma)\tan(\sigma - s)d\sigma + \sum_{j=1}^{2} \operatorname*{res}_{\sigma=\theta_j}[F_{2e}(\sigma)\tan(\sigma - s)]$$

$$+ \sum_{j=1}^{n_2'} \operatorname*{res}_{\sigma = s_{ej}^{(2R)}}[F_{2e}(\sigma)\tan(\sigma - s)], \quad \frac{\pi}{2} < \operatorname{Re} s < \frac{3\pi}{2}. \tag{6.24}$$

It will be convenient to use the following notations

$$M_e^\pm = \frac{i\hat{\Phi}_1^\pm(k_0\sin\theta_0)}{2k_0\sin\theta_0} + \frac{i}{2k_0^2\sin 2\theta_0}\Big\{(\gamma_1^- \pm k_0\sin\theta_0)[\hat{\Psi}_1^+(k_0\cos\theta_0) - \hat{\Psi}_1^-(k_0\cos\theta_0)]$$

$$+k_0\cos\beta\cos\theta_0[\hat{\Psi}_2^+(k_0\cos\theta_0) + \hat{\Psi}_2^-(k_0\cos\theta_0)]\Big\},$$

$$N_{ej}^{(2R)} = \operatorname*{res}_{s = s_{ej}^{(2R)}} F_{2e}(s). \tag{6.25}$$

On employing now formulas (6.6) and (6.14) we arrive at the analytic continuation into the strip $\pi/2 < \operatorname{Re} s < 3\pi/2$ of the function $S_e^{(2)}(s)$. It has the form

$$S_e^{(2)}(s) = -\frac{1}{2\pi i}\int_{-i\infty}^{i\infty} F_{2e}(\sigma + \pi)\tan(\sigma - s)d\sigma + M_e^-\cot(s - \theta_0)$$

$$- M_e^+\cot(s + \theta_0) - \sum_{j=1}^{n_2'} N_{ej}^{(2R)}\tan(s - s_{ej}^{(2R)}), \quad \frac{\pi}{2} < \operatorname{Re} s < \frac{3\pi}{2}. \tag{6.26}$$

To describe all surface waves, we need to continue the function $S_e^{(2)}$ further to the right up to the line $\operatorname{Im} s = 2\pi$. In the strip $\pi < \operatorname{Re} s < 3\pi/2$, the function $F_{2e}(s)$ has one geometric optics pole $3\pi/2 - \theta_0$ and poles $s_{ej}^{(2R)}$ $(j = n_2' + 1, \ldots, n_2)$ which may generate surface waves. By shifting the contour to the right by $\pi/2$, similarly to (6.26) we obtain

$$S_e^{(2)}(s) = \frac{1}{2\pi i} \int_{-i\infty}^{i\infty} F_{2e}\left(\sigma + \frac{3\pi}{2}\right) \cot(\sigma - s) d\sigma + M_e^- \cot(s - \theta_0)$$

$$+ (M_e^- - M_e^+) \cot(s + \theta_0) - \sum_{j=1}^{n_2} N_{ej}^{(2R)} \tan(s - s_{ej}^{(2R)}), \quad \frac{3\pi}{2} < \operatorname{Re} s < 2\pi. \tag{6.27}$$

Analyze next the function $S_e^{(1)}(s)$ given by (6.13). It is analytic in the strip $0 < \operatorname{Re} s < \pi$ and can be continued analytically into the strip $\pi < \operatorname{Re} s < 2\pi$ by shifting the contour $\operatorname{Re} s = 0$ to the right by π. In the strip $0 < \operatorname{Re} s < \pi$, the function $F_{1e}(s)$ has simple poles at the points θ_0 and $\pi - \theta_0$. In addition, it may have surface wave poles at the zeros of $\tilde{d}(k_0 \cos s)$ in the domain $0 < \operatorname{Re} s < \pi$, $\operatorname{Im}(k_0 \cos s) < 0$ and the zeros of $d(k_0 \sin s)$ in the strip $0 < \operatorname{Re} s < \pi$. Denote these poles by $s_{ej}^{(1R)}$ $(j = 1, \ldots, n_1)$. The analytic continuation of the function $S_e^{(1)}(s)$ into the strip $\pi < \operatorname{Re} s < 2\pi$ eventually gives

$$S_e^{(1)}(s) = -\frac{1}{2\pi i} \int_{-i\infty}^{i\infty} F_{1e}(\sigma + \pi) \cot(\sigma - s) d\sigma + \Lambda_e^+ \cot(s - \theta_0)$$

$$- \Lambda_e^- \cot(s + \theta_0) - \sum_{j=1}^{n_1} N_{ej}^{(1R)} \cot(s - s_{ej}^{(1R)}), \quad \pi < \operatorname{Re} s < 2\pi, \tag{6.28}$$

where

$$\Lambda_e^{\pm} = \frac{i \hat{\Psi}_1^{\pm}(k_0 \cos\theta_0)}{2k_0 \cos\theta_0} + \frac{i}{2k_0^2 \sin 2\theta_0} \Big\{ (\gamma_1^+ \pm k_0 \cos\theta_0)[\hat{\Phi}_1^+(k_0 \sin\theta_0) - \hat{\Phi}_1^-(k_0 \sin\theta_0)]$$

$$-k_0 \cos\beta \sin\theta_0 [\hat{\Phi}_2^+(k_0 \sin\theta_0) + \hat{\Phi}_2^-(k_0 \sin\theta_0)] \Big\},$$

$$N_{ej}^{(1R)} = \operatorname*{res}_{\sigma = s_{ej}^{(1R)}} F_{1e}(\sigma). \tag{6.29}$$

After combining formulas (6.12), (6.13), (6.26) to (6.28) we obtain the representations of the function $S_e(s)$ in the strip $0 < \operatorname{Re} s < 2\pi$. Let

$$I_{je}^c(s, a) = -\frac{1}{2\pi i} \int_{-i\infty}^{i\infty} F_{je}(\sigma + a) \cot(\sigma - s) d\sigma, \quad a < \operatorname{Re} s < \pi + a,$$

$$I_{je}^t(s, a) = -\frac{1}{2\pi i} \int_{-i\infty}^{i\infty} F_{je}(\sigma + a) \tan(\sigma - s) d\sigma, \quad -\pi/2 + a < \operatorname{Re} s < \pi/2 + a. \tag{6.30}$$

Then we may write

$$S_e(s) = I_{1e}^c(s, 0) + I_{2e}^t(s, 0) + E_0[\cot(s - \theta_0) - \cot(s + \theta_0)], \quad 0 < \operatorname{Re} s < \frac{\pi}{2},$$

$$S_e(s) = I_{1e}^c(s, 0) + I_{2e}^t(s, \pi) + (E_0 + M_e^-) \cot(s - \theta_0)$$

$$- (E_0 + M_e^+) \cot(s + \theta_0) - \sum_{j=1}^{n_2''} N_{ej}^{(2R)} \tan(s - s_{ej}^{(2R)}), \quad \frac{\pi}{2} < \operatorname{Re} s < \pi, \tag{6.31}$$

where $s_{ej}^{(2R)}$ $(j=1,2,\dots,n_2'')$ are the surface wave poles of $F_{2e}(s)$ in the domain $0<\operatorname{Re}s<\pi/2$,

$$S_e(s)=I_{1e}^c(s,\pi)+I_{2e}^t(s,\pi)+(E_0+M_e^-+\Lambda_e^+)\cot(s-\theta_0)-(E_0+M_e^++\Lambda_e^-)\cot(s+\theta_0)$$

$$-\sum_{j=1}^{n_1'}N_{ej}^{(1R)}\cot(s-s_{ej}^{(1R)})-\sum_{j=1}^{n_2'}N_{ej}^{(2R)}\tan(s-s_{ej}^{(2R)}),\quad \pi<\operatorname{Re}s<\frac{3\pi}{2}, \tag{6.32}$$

where $s_{ej}^{(1R)}$ $(j=1,2,\dots,n_1')$ are the surface wave poles of $F_{1e}(s)$ in the domain $0<\operatorname{Re}s<\pi/2$. Finally, as $3\pi/2<\operatorname{Re}s<2\pi$,

$$S_e(s)=I_{1e}^c(s,\pi)-I_{2e}^c\left(s,\frac{3\pi}{2}\right)+(E_0+M_e^-+\Lambda_e^+)\cot(s-\theta_0)$$

$$-(E_0+M_e^+-M_e^-+\Lambda_e^-)\cot(s+\theta_0)-\sum_{j=1}^{n_1}N_{ej}^{(1R)}\cot(s-s_{ej}^{(1R)})-\sum_{j=1}^{n_2}N_{ej}^{(2R)}\tan(s-s_{ej}^{(2R)}). \tag{6.33}$$

To recover the reflected, surface and diffracted waves, we also need to continue the function $S_e(s)$ to the strip $-3\pi/2<\operatorname{Re}s<0$. In the strip $-\pi<\operatorname{Re}s<0$, the function $F_{1e}(s)$ has poles at the points $-\theta_0$, $-\pi+\theta_0$ (the geometric optics poles) and may have surface wave poles at the zeros of $\tilde{d}(k_0\cos s)$ in the domain $-\pi<\operatorname{Re}s<0, \operatorname{Im}(k_0\cos s)<0$ and at the zeros of $d(k_0\sin s)$ in the strip $-\pi<\operatorname{Re}s<0$. Denote the residues of $F_{1e}(s)$ at the surface wave poles, $s_{ej}^{(1L)}$, as $N_{ej}^{(1L)}$ $(j=1,\dots,m_1')$. This brings us to

$$S_e^{(1)}(s)=-\frac{1}{2\pi i}\int_{-i\infty}^{i\infty}F_{1e}(\sigma-\pi)\cot(\sigma-s)d\sigma+\Lambda_e^-\cot(s-\theta_0)$$

$$-\Lambda_e^+\cot(s+\theta_0)+\sum_{j=1}^{m_1'}N_{ej}^{(1L)}\cot(s-s_{ej}^{(1L)}),\quad -\pi<\operatorname{Re}s<0. \tag{6.34}$$

By shifting the contour of integration further to the left by $\pi/2$ we find the analytical continuation of the function $S_e^{(1)}(s)$ into the strip $-3\pi/2<\operatorname{Re}s<\pi$. In doing so we take into account the poles of $F_{1e}(s)$ at $s=-\pi-\theta_0$ and $s_{ej}^{(1L)}$ with the residues $N_{ej}^{(1L)}$ $(j=m_1'+1,\dots,m_1)$.

The analytical continuation of $S_{e2}(s)$ from the strip $-\pi/2<\operatorname{Re}s<\pi/2$ into the strip $-3\pi/2<\operatorname{Re}s<-\pi/2$ is implemented by shifting the contour of integration in (6.13) to the left by π. The poles of $F_{2e}(s)$ in the strip $-\pi<\operatorname{Re}s<0$ comprise the the geometric optics poles $-\pi/2+\theta_0$ and $-\pi/2-\theta_0$ and the surface wave poles $s_{ej}^{(2L)}$ with the residues $N_{ej}^{(2L)}$ $(j=1,\dots,m_2)$ at the zeros of $d(k_0\cos s)$ in the domain $-\pi<\operatorname{Re}s<0, \operatorname{Im}(k_0\cos s)<0$ and at the zeros of $\tilde{d}(k_0\sin s)$ in the strip $-\pi<\operatorname{Re}s<0$. This enables us to write the analytical continuation of the function $S_e(s)$ into the strip $-3\pi/2<\operatorname{Re}s<0$ as

$$S_e(s)=I_{1e}^c(s,-\pi)+I_{2e}^t(s,0)+(E_0+\Lambda_e^-)\cot(s-\theta_0)$$

$$-(E_0+\Lambda_e^+)\cot(s+\theta_0)+\sum_{j=1}^{m_1''}N_{ej}^{(1L)}\cot(s-s_{ej}^{(1L)}),\quad -\frac{\pi}{2}<\operatorname{Re}s<0,$$

$$S_e(s)=I_{1e}^c(s,-\pi)+I_{2e}^t(s,-\pi)+(E_0+\Lambda_e^-+M_e^+)\cot(s-\theta_0)-(E_0+\Lambda_e^++M_e^-)\cot(s+\theta_0)$$

$$+\sum_{j=1}^{m_1'}N_{ej}^{(1L)}\cot(s-s_{ej}^{(1L)})+\sum_{j=1}^{m_2'}N_{ej}^{(2L)}\tan(s-s_{ej}^{(2L)}),\quad -\pi<\operatorname{Re}s<-\frac{\pi}{2},$$

$$
\begin{aligned}
S_e(s) = -I^t_{1e}\left(s, -\frac{3\pi}{2}\right) + I^t_{2e}(s, -\pi) + (E_0 + \Lambda^-_e + M^+_e)\cot(s - \theta_0) \\
-(E_0 + \Lambda^+_e - \Lambda^-_e + M^-_e)\cot(s + \theta_0) \\
+\sum_{j=1}^{m_1} N^{(1L)}_{ej}\cot(s - s^{(1L)}_{ej}) + \sum_{j=1}^{m_2} N^{(2L)}_{ej}\tan(s - s^{(2L)}_{ej}), \quad -\frac{3\pi}{2} < \operatorname{Re} s < -\pi. \qquad (6.35)
\end{aligned}
$$

Here, $s^{(1L)}_{ej}$ $(j = 1, \ldots, m''_1)$ and $s^{(2L)}_{ej}$ $(j = 1, \ldots, m'_2)$ are the surface wave poles of the functions $F_{1e}(s)$ and $F_{2e}(s)$, respectively, in the domain $-\pi/2 < \operatorname{Re} s < 0$.

In the case of the function $S_h(s)$ all the formulas derived can still be used if we replace β by $\pi - \beta$ and interchange the parameters $\gamma^\pm_1$ with $\gamma^\pm_4$, the functions $\Phi^\pm_1(s)$, $\Psi^\pm_1$ with $\Phi^\pm_2(s)$, $\Psi^\pm_2$, respectively. The constants $\Lambda^\pm_e$, and $M^\pm_e$ corresponding to the function $S_h(s)$ are denoted by $\Lambda^\pm_h$ and $M^\pm_h$.

6.2 Incident, reflected, surface and diffracted waves

Let $\mathcal{C}$ be a closed contour that comprises the Sommerfeld contours $\mathcal{T}_+$ and $\mathcal{T}_-$ and two contours $\mathcal{G}_L$ and $\mathcal{G}_R$. The starting points of the contours $\mathcal{G}_L$ and $\mathcal{G}_R$ are $-3\pi/2 + i\infty$ and $3\pi/2 - i\infty$, and they pass through the points $s = -\pi$ and $s = \pi$, respectively. The contour $\mathcal{G}_R$ is described by the equation $\operatorname{Re} s = \pi - \operatorname{gd}(\operatorname{Im} s)\operatorname{sgn}(\operatorname{Im} s)$, and the contour $\mathcal{G}_L$ is symmetric to $\mathcal{G}_R$ with respect to the origin. Here, $\operatorname{gd} x$ is the Gudermann function $\operatorname{gd} x = \cos^{-1}\operatorname{sech} x$. As $k_0 r \to \infty$, the electric and magnetic field can be represented as

$$
\begin{aligned}
E_z \sim E^i_z + E^r_z + E^s_z + E^d_z, \\
H_z \sim H^i_z + H^r_z + H^s_z + H^d_z, \quad kr \to \infty, \qquad (6.36)
\end{aligned}
$$

where E^i_z, H^i_z are the incident waves, E^r_z, H^r_z are the reflected waves, E^s_z, H^s_z are the surface waves, and E^d_z, H^d_z are the diffracted waves.

Write down first those poles of the functions $S_e(s)$ and $S_h(s)$ which are in the interval $(-\pi, \pi)$ and which generate the incident and reflected waves. These poles are

$$
\begin{aligned}
s = -\theta + \theta_0 \in (-\pi/2, \pi/2), \quad s + \theta \in (0, \pi/2), \\
s = \pi - \theta - \theta_0 \in (0, \pi), \quad s + \theta \in (\pi/2, \pi), \\
s = -\theta - \theta_0 \in (-\pi, 0), \quad s + \theta \in (-\pi/2, 0), \\
s = \pi - \theta + \theta_0 \in (\pi/2, \pi) \text{ if } \theta_0 < \theta < \pi/2, \quad s + \theta \in (\pi, 3\pi/2), \\
s = -\pi - \theta + \theta_0 \in (-\pi, -\pi/2) \text{ if } 0 < \theta < \theta_0, \quad s + \theta \in (-\pi, -\pi/2). \qquad (6.37)
\end{aligned}
$$

The incident and reflected electrical and magnetic waves can be recovered from (6.1), (6.31), (6.32) and (6.35)

$$
\begin{aligned}
E^i_z = E_0 e^{-ik_0\rho\cos(\theta-\theta_0)}, \quad H^i_z = H_0 e^{-ik_0\rho\cos(\theta-\theta_0)}, \\
E^r_z = -(E_0 + \Lambda^+_e)e^{-ik_0\rho\cos(\theta+\theta_0)} - (E_0 + M^+_e)e^{ik_0\rho\cos(\theta+\theta_0)} \\
+\omega(\theta; 0, \theta_0)(E_0 + \Lambda^-_e + M^+_e)e^{ik_0\rho\cos(\theta-\theta_0)} + \omega(\theta; \theta_0, \pi/2)(E_0 + \Lambda^+_e + M^-_e)e^{ik_0\rho\cos(\theta-\theta_0)}, \\
ZH^r_z = -(ZH_0 + \Lambda^+_h)e^{-ik_0\rho\cos(\theta+\theta_0)} - (ZH_0 + M^+_h)e^{ik_0\rho\cos(\theta+\theta_0)} \\
+\omega(\theta; 0, \theta_0)(ZH_0 + \Lambda^-_h + M^+_h)e^{ik_0\rho\cos(\theta-\theta_0)} + \omega(\theta; \theta_0, \pi/2)(ZH_0 + \Lambda^+_h + M^-_h)e^{ik_0\rho\cos(\theta-\theta_0)}, \quad (6.38)
\end{aligned}
$$

where

$$
\omega(\theta; a, b) = \begin{cases} 1, \ a < \theta < b, \\ 0, \ \text{otherwise}. \end{cases} \qquad (6.39)
$$

To recover the surface waves we select those surface wave poles which meet the conditions

$$0 < \mathrm{Re}(-\theta + s_{ej}^{(lR)}) < \pi - g_j^{(lR)}, \quad j = 1, 2, \dots, \tilde{n}_l \le n_l, \quad l = 1, 2,$$

$$-\pi - g_j^{(lL)} < \mathrm{Re}(-\theta + s_{ej}^{(lL)}) < 0, \quad j = 1, 2, \dots, \tilde{m}_l \le m_l, \quad l = 1, 2, \tag{6.40}$$

where $g_j^{(lP)} = \mathrm{gd}(\mathrm{Im}\, s_{ej}^{(lP)}) \,\mathrm{sgn}(\mathrm{Im}\, s_{ej}^{(lP)})$, $P = R, L$. Denote these surface wave poles as $\tilde{s}_{ej}^{(lR)}$ $(\mathrm{Re}\, s_{ej}^{(lR)} > 0, j = 1, \dots, \tilde{n}_l)$ and $\tilde{s}_{ej}^{(lL)}$ $(\mathrm{Re}\, s_{ej}^{(lL)} < 0, j = 1, \dots, \tilde{m}_l)$, and the associated residues as $\tilde{N}_{ej}^{(lR)}$ and $\tilde{N}_{ej}^{(lL)}$, respectively. Let

$$\lambda_{ej}^{(lR)} = \max\{0, -\pi + g_j^{(lR)} + \mathrm{Re}(\tilde{s}_{ej}^{(lR)})\}, \quad \lambda_{ej}^{(lL)} = \min\{\pi/2, \pi + g_j^{(lL)} + \mathrm{Re}(\tilde{s}_{ej}^{(lL)})\}. \tag{6.41}$$

We note that the poles $s_{ej}^{(lR)}$ and $s_{ej}^{(lL)}$ generate the surface waves if and only if $-\pi + g_j^{(lR)} + \mathrm{Re}(\tilde{s}_{ej}^{(lR)}) < \pi/2$ and $\pi + g_j^{(lL)} + \mathrm{Re}(\tilde{s}_{ej}^{(lL)}) > 0$, respectively. By making use of (6.1), (6.31), (6.32) and (6.35) we write down the surface waves E_z^s and H_z^s as

$$E_z^s = \sum_{l=1}^{2} \left[-\sum_{j=1}^{\tilde{n}_l} \tilde{N}_{ej}^{(lR)} \omega(\theta, \lambda_{ej}^{(lR)}, \pi/2) \exp\{-ik_0\rho \cos(\theta - \tilde{s}_{ej}^{(lR)})\} \right.$$
$$\left. + \sum_{j=1}^{\tilde{m}_l} \tilde{N}_{ej}^{(lL)} \omega(\theta, 0, \lambda_{ej}^{(lL)} \exp\{-ik_0\rho \cos(\theta - \tilde{s}_{ej}^{(lL)})\} \right],$$

$$ZH_z^s = \sum_{l=1}^{2} \left[-\sum_{j=1}^{\hat{n}_l} \tilde{N}_{hj}^{(lR)} \omega(\theta, \lambda_{hj}^{(lR)}, \pi/2) \exp\{-ik_0\rho \cos(\theta - \tilde{s}_{hj}^{(lR)})\} \right.$$
$$\left. + \sum_{j=1}^{\hat{m}_l} \tilde{N}_{hj}^{(lL)} \omega(\theta, 0, \lambda_{hj}^{(lL)} \exp\{-ik_0\rho \cos(\theta - \tilde{s}_{hj}^{(lL)})\} \right], \tag{6.42}$$

where $\hat{n}_l$, $\hat{m}_l$, $\lambda_{hj}^{(lR)}$ and $\lambda_{hj}^{(lR)}$ are the counterparts of the corresponding numbers $\tilde{n}_l$, $\tilde{m}_l$, $\lambda_{ej}^{(lR)}$ and $\lambda_{ej}^{(lR)}$ in the magnetic case.

The diffracted waves are determined in a standard manner in the form

$$E_z^d = \frac{e^{ik_0\rho}}{\sqrt{k_0\rho}} D_e(\theta), \quad ZH_z^d = \frac{e^{ik_0\rho}}{\sqrt{k_0\rho}} D_h(\theta), \tag{6.43}$$

where $D_e(\theta)$ and $D_h(\theta)$ are the diffraction coefficients

$$D_e(\theta) = \frac{e^{-i\pi/4}}{\sqrt{2\pi}} [S_e(\theta - \pi) - S_e(\theta + \pi)], \quad D_h(\theta) = \frac{e^{-i\pi/4}}{\sqrt{2\pi}} [S_h(\theta - \pi) - S_h(\theta + \pi)]. \tag{6.44}$$

Conclusions

We have found a closed-form solution of the classical problem on scattering of an electromagnetic plane obliquely incident wave from an impedance wedge in the right-angled concave case. By splitting the incident wave into two waves, the one that strikes the vertical wall and the other that impinges upon the horizontal face of the wedge, we have reduced the boundary value problem for the Helmholtz equation to two vector RHPs subject to the symmetry condition for the unknown vectors, $\Phi^+(\eta) = \Phi^-(-\eta)$. The matrix factorization problem has been solved by the technique of the RHP on a genus-3 Riemann surface in the case of the boundary conditions (1.1). In the general case (1.2) of the boundary conditions the matrix can be factorized as well. However, this requires tedious computations of the analogues of formulas (3.22), (4.1) and (4.2). Due to the symmetry of the problem we have managed to avoid the genus-3 Riemann θ-function and to solve the Jacobi inversion problem in terms of elliptic functions. The Wiener-Hopf matrix-factors have been found by quadratures and, eventually, a closed-form solution to the two vector RHPs associated with the diffraction problem of interest has been constructed. In addition, we have proved the uniqueness theorem (Theorem 5.1) which generalizes the known result in the scalar case (see for example **(18)**) to the vectorial case. The solution is unique when all the four zeros of the characteristic polynomial (5.65) of the problem lie in the upper half-plane and has n arbitrary constants with n being the number of the zeros lying in the lower half-plane. In the uniqueness case we have shown how to express the spectra of the problem and therefore the Sommerfeld integrals through the solution of the two vector RHPs. By using these expressions we have analytically continued the spectra to the left and to the right and by steepest descent method recovered the incident, reflected, surface and diffracted waves.

References

1. G. D. Maliuzhinets, Excitation, reflection and emission of surface waves from a wedge with given face impedances, *Sov. Phys. Dokl.* **3** (1958) 752-755.
2. R. A. Hurd and E. Luneburg, Diffraction by an anisotropic impedance half plane, *Canad. J. Phys.* **63** (1985) 1135-1140.
3. E. Lüneburg and A. H. Serbest, Diffraction of an obliquely incident plane wave by a two-face impedance half plane: Wiener-Hopf approach, *Radio Sci.* **35** (2000) 1361-1374.
4. Y. A. Antipov and V. V. Silvestrov, Electromagnetic scattering from an anisotropic impedance half plane at oblique incidence: the exact solution, *Quart. J. Mech. Appl. Math.* **59** (2006) 211-251.
5. J. M. L. Bernard, Diffraction at skew incidence by an anisotropic wedge in electromagnetism theory: a new class of canonical cases, *J. Phys. A: Math. Gen.* **31** (1998) 595-613.
6. M. A. Lyalinov and N. Y. Zhu, Exact solution to diffraction problem by wedges with a class of anisotropic impedance faces: oblique incidence of a plane electromagnetic wave, *IEEE Trans. Antenn. Propag.* **51** (2003) 1216-1220.
7. H. H. Syed and J. L. Volakis, An approximate solution for scattering by an impedance wedge at skew incidence, *Radio Sci.* **30** (1995) 505-524.
8. G. Pelosi, G. Manara and P. Nepa, A UTD solution for the scattering by a wedge with anisotropic impedance faces: skew incidence case *IEEE Trans. Antenn. Propag.* **46** (1998) 579-588.
9. M. A. Lyalinov and N. Y. Zhu, Diffraction of a skew incident plane electromagnetic wave by an impedance wedge, *Wave Motion* **44** (2006) 21-43.
10. Y. A. Antipov and V. V. Silvestrov, Method of integral equations for systems of difference equations, *IMA J. Appl. Math.* **72** (2007) 681-705.
11. V. G. Daniele and G. Lombardi, Wiener-Hopf solution for impenetrable wedges at skew Incidence, *IEEE Trans. Antenn. Propag.* **54** (2006) 2472-2485.

12. B. Budaev and D. B. Bogy, Diffraction of a plane skew electromagnetic wave by a wedge with general anisotropic impedance boundary conditions, *IEEE Trans. Antenn. Propag.* **54** (2006) 1559-1567.
13. A. V. Osipov and T. B. A. Senior, Diffraction and reflection of a plane electromagnetic wave by a right-angled impedance wedge, *IEEE Trans. Antenn. Propag.* **57** (2009) 1789-1803.
14. A. V. Osipov and T.B.A. Senior, Electromagnetic diffraction by arbitrary-angle impedance wedges, *Proc. Roy. Soc. A* **464** (2008) 177-195.
15. V. G. Daniele, The Wiener-Hopf technique for impenetrable wedges having arbitrary aperture angle, *SIAM J. Appl. Math.* **63** (2003) 1442-1460.
16. Y. A. Antipov, A symmetric Riemann-Hilbert problem for order-4 vectors in diffraction theory, *Quart. J. Mech. Appl. Math.* **63** (2010) 349-374.
17. Y. A. Antipov, A genus-3 Riemann-Hilbert problem and diffraction of a wave by orthogonal resistive half-planes, *Comput. Meth. Function Theory* **11** (2011) 439-462.
18. V. M. Babich, M. A. Lyalinov and V. E. Grikurov, *Diffraction theory: the Sommerfeld-Malyuzhinets technique* (Alpha Science, Oxford, 2008).
19. H. Hancock, *Lectures on the Theory of Elliptic Functions* (Dover, New York 1968).
20. G. D. Maliuzhinets, Relation between the inversion formulas for the Sommerfeld integral and the formulas of Kontorovich-Lebedev, *Sov. Phys. Dokl.* **3** (1958) 266-268.